



**austriamicrosystems AG**

**is now**

**ams AG**

The technical content of this austriamicrosystems datasheet is still valid.

**Contact information:**

**Headquarters:**

ams AG

Tobelbaderstrasse 30

8141 Unterpremstaetten, Austria

Tel: +43 (0) 3136 500 0

e-Mail: [ams\\_sales@ams.com](mailto:ams_sales@ams.com)

Please visit our website at [www.ams.com](http://www.ams.com)



## Pin Description

| Pin # | Symbol | Function                                                                                                                                                                                                                                                       |
|-------|--------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| 15    | RFD    | <b>R</b> ing <b>F</b> requency <b>D</b> iscrimination<br>Schmitt trigger input for ring frequency discrimination. Disabled during off-hook.                                                                                                                    |
| 7     | LS     | <b>L</b> ine <b>C</b> urrent <b>S</b> ense Input<br>Input for sensing the line current                                                                                                                                                                         |
| 5     | LI     | <b>L</b> ine <b>I</b> nput<br>Input used for power extraction and line current sensing                                                                                                                                                                         |
| 6     | RI     | <b>R</b> ecieve <b>I</b> nput<br>Input for ac-separated receive signal                                                                                                                                                                                         |
| 2     | STB    | <b>S</b> ide <b>T</b> one <b>B</b> alance Input<br>Input for side tone cancellation network                                                                                                                                                                    |
| 3     | CS     | <b>C</b> urrent <b>S</b> hunt Control Output<br>N-channel open drain output to control the external high power shunt transistor for synthesising ac- and dc- impedance, modulation of line voltage and shorting the line during make periods of pulse dialling |
| 8     | CI     | <b>C</b> omplex <b>I</b> mpedance Input<br>Input pin for the capacitor to program a complex impedance                                                                                                                                                          |
| 16    | DPn    | <b>D</b> ial <b>P</b> ulse Output<br>Open drain output pulls low during break periods of pulse dialling and flash                                                                                                                                              |
| 17    | EHS    | <b>E</b> lectronic <b>H</b> ook <b>S</b> witch<br>Schmitt Trigger Input to detect an electronic off-hook.                                                                                                                                                      |
| 18    | MHS    | <b>M</b> anual <b>H</b> ook <b>S</b> witch<br>Schmitt Trigger Input to detect a manual off-hook.                                                                                                                                                               |
| 19    | MODE   | <b>D</b> TMF <b>L</b> evel <b>S</b> election<br>-4/-6dBm → DLS open<br>-6/-8dBm → DLS-r1<br>-8/-10dBm → DLS-r2<br><br><b>L</b> ine <b>L</b> oss <b>C</b> ompensation Select Pin<br>45mA-75mA → LLC open<br>20mA-50mA → LLC-r3<br>None → LLC-r4                 |
| 28    | MO     | Ring <b>M</b> elody <b>O</b> utput<br>PDM output of the ring melody generator.                                                                                                                                                                                 |
| 11    | VDD    | <b>V</b> oltage <b>D</b> rain <b>D</b> rain<br>Positive Power Supply                                                                                                                                                                                           |
| 4     | VSS    | <b>V</b> oltage <b>S</b> ource <b>S</b> ource<br>Negative Power Supply                                                                                                                                                                                         |

| Pin #          | Symbol         | Function                                                                                                                                       |
|----------------|----------------|------------------------------------------------------------------------------------------------------------------------------------------------|
| 25             | OSC            | <b>O</b> scillator Input<br>Input for ceramic resonator 3.58MHz.<br>Recommended type: Murata CSA 3.58MG312AM or compatible                     |
| 12             | AGND           | <b>A</b> nalogue <b>G</b> round<br>Special ground for the internal amplifiers                                                                  |
| 26             | RXD            | <b>R</b> ecieve <b>D</b> ata Input<br>Schmitt trigger input to serial interface                                                                |
| 27             | TXD            | <b>T</b> ransmit <b>D</b> ata Output<br>Open drain output from serial interface                                                                |
| 20<br>21       | R1<br>R2       | Keyboard <b>R</b> ows                                                                                                                          |
| 22<br>23<br>24 | C1<br>C2<br>C3 | Keyboard <b>C</b> olumns                                                                                                                       |
| 10             | ROT            | <b>R</b> ecieve <b>O</b> utput to <b>T</b> ransformer<br>Output for driving a transformer with an ac impedance larger than 10k $\Omega$        |
| 1              | TIT            | <b>T</b> ransformer <b>I</b> nput from <b>T</b> ransformer<br>Single ended input for transformer                                               |
| 9              | ROH            | <b>R</b> ecieve <b>O</b> utput to <b>H</b> andset<br>Output for driving a dynamic earpiece with an impedance from 150 $\Omega$ to 300 $\Omega$ |
| 13<br>14       | M2<br>M1       | <b>M</b> icrophone Inputs<br>Differential inputs for the microphone (electret)                                                                 |

## Functional Description

## Modes of operation

There are 4 possible modes:

## Idle Mode

Manual hook-switch and electronic hook-switch (e.g. relay) is open ( $MHS \cap EHS = \text{logical } 0$ ), no ring signal is applied, the oscillator is stopped, signalling via the serial interface is not possible.

## Ringling Mode

AS2540 is supplied via the ring capacitor and external path, manual hook-switch and electronic hook-switch is open ( $MHS \cap EHS = \text{logical } 0$ ), the oscillator is running, a valid incoming ringing is signalled via the serial interface to the CPU. If the CPU does not reply the AS2540 switches into backup mode and sends a ring melody to the MO output.

## Backup Mode

Manual hook-switch and/or electronic hook-switch is closed (MHS  $\cup$  EHS = logical 1), AS2540 is supplied with line current, the oscillator is running, the keyscan is enabled and the handset path is switched on, signalling via the serial interface is possible. After AS2540 has started dialling in backup mode, he must not be interrupted any more in order to ensure consistent dialling. A mode transition BM  $\rightarrow$  MPM is only possible before AS2540 has started dialling digits independently.


## Main Power Mode

Manual hook-switch and/or electronic hook-switch is closed, AS2540 is supplied with line current (MHS  $\cup$  EHS = logical 1), the oscillator is running, the keyscan is disabled, AS2540 is controlled via the serial interface, handset path or monitor path or modem path is on, signalling via the serial interface is possible.

### Select Operation Mode

| Command Message  | Switches ON | Switches OFF |
|------------------|-------------|--------------|
| <SetHandsetPath> | SROH        | SROT & STIT  |
| <SetModemPath>   | SROT & STIT |              |
| <SetMonitorPath> | SROH & SROT | STIT         |

### Example Main Power Mode



## Start-up in backup mode

As soon as AS2540 is supplied with line current, the external Vdd capacitor will be charged up via the LI and VDD pin and after the Vdd voltage has reached the operating level, the handset path of the speech circuit is switched on. This off-hook status is also signalled to the internal logic via the MHS or EHS pin in order to start the pinscan and subsequently set the country specific modes. Additionally a <LineEvent> message is sent to the CPU.

## Start-up in ring mode

When a ringing signal is applied to the line, Vdd of AS2540 is charged up via an external path. After Vdd has reached the operating voltage the oscillator starts and AS2540 discriminates the ring frequency. After a valid ring frequency is applied on the RFD pin, the logic sends a <LineEvent> message to the CPU and a watchdog timer is started. When the <LineEvent> message is not quit by the CPU before the watchdog timer has finished the countdown, AS2540 changes into backup mode and sends out a melody via the MO pin.


## DC conditions

The normal operating mode is from 15mA to 100mA. An operating mode with reduced performance is from 5mA to 15mA. In the line hold range from 0mA to 5mA the device is in a power down mode and the voltage at LI is reduced to a maximum of 3.5V

The DC characteristic is determined by the voltage at LI pin and a 30Ω resistor between LI and LS pin. It can be calculated by the following equation:  $V_{LS} = V_{LI} + I_{Line} \cdot 30\Omega$ . The t.m. voltage at the LI pin is 4.5V. The calculation leads to the following DC resistances: 330Ω to 75Ω at line currents from 15mA to 100mA.

## 2/4 wire conversion

AS2540 has a built-in dual Wheatstone bridge with one common ground. This provides a maximum of independence of AC impedance and side tone from each other. One can adapt side tone without changing the AC impedance.



A1=3.4/3.5

A2=-0.4

## AC impedance

The ac impedance of AS2540 is set to t.m. 1000Ω. With the external capacitor at C1 pin it can be programmed complex. With a parallel impedance at the LS pin it can be programmed to 600Ω.

## Side Tone

A good sidetone cancellation can be achieved by using the following equation:

$$Z_{BAL}/Z_{LINE} = 10$$

## Transmit path

The gain of the M1/M2 → LS transmit path is set to 38dB for ac-impedance 1000Ω. The input is differential with an impedance of 25kΩ. The soft clip circuit limits the output voltage at LS to 2Vp. The attack time is 30μs/6dB and the decay time is 20ms/6dB.

The gain of the TIT → LS transmit path is set to 8dB for ac-impedance 1000Ω. The input is single ended with an impedance of 25kΩ. The soft clip circuit is not active for this input. The dynamic range of this path is 2.5Vp at LS.


## Receive path

The gain of the LS → ROH receive path is set to 2dB for ac-impedance 1000Ω. The receive input is the differential signal of RI and STB. During DTMF dialling a MF comfort tone is applied to ROH which is -30dB relative to the line level. The soft clip circuit limits the output voltage at ROH to 1Vp. It prevents harsh distortion and acoustic shock.

The gain of the LS → ROT receive path is set to 0dB for ac-impedance 1000Ω. The receive input is the differential signal of RI and STB. The soft clip circuit is not active for this output.

## Modescan

The DTMF-level on the line and the function of the line loss compensation can be selected with the connection of the MODE-pin to the keyboard matrix. The MODE-pin is scanned once after each OFF-Hook transition.



| C3 | C2 | C1 | R2 | R1 | LLC       | Dtmf Level |
|----|----|----|----|----|-----------|------------|
|    |    |    |    |    | 45mA-75mA | -6dBm      |
|    |    |    | X  | X  | 45mA-75mA | -8dBm      |
|    |    | X  |    |    | 45mA-75mA | -10dBm     |
|    | X  |    |    |    | 20mA-50mA | -6dBm      |
| X  |    |    |    |    | 20mA-50mA | -8dBm      |
|    | X  | X  |    |    | 20mA-50mA | -10dBm     |
| X  |    | X  |    |    | No LLC    | -6dBm      |
| X  | X  |    |    |    | No LLC    | -8dBm      |
| X  | X  | X  |    |    | No LLC    | -10dBm     |

X indicates connection to pin mode

## Serial interface

The communication principle is derived from a standard UART:

- Baud Rate      9600
- Start Bit       1
- Data Bits       8
- Parity           None
- Stop Bit        1
- LSB is transferred prior to MSB

### Rx - messages

#### Message Format

|     |   |    |    |    |    |    |     |
|-----|---|----|----|----|----|----|-----|
| X   | X | d5 | d4 | d3 | d2 | d1 | 1   |
| MSB |   |    |    |    |    |    | LSB |

| d7 | d6 | d5 | d4 | d3 | d2 | d1 | d0 | DTMF-dial message | Notes                         |
|----|----|----|----|----|----|----|----|-------------------|-------------------------------|
| x  | x  | 0  | 1  | 0  | 1  | 0  | 1  | Digit 0           | Starts DTMF dialling of digit |
| x  | x  | 0  | 0  | 0  | 0  | 1  | 1  | Digit 1           | Starts DTMF dialling of digit |
| x  | x  | 0  | 0  | 0  | 1  | 0  | 1  | Digit 2           | Starts DTMF dialling of digit |
| x  | x  | 0  | 0  | 0  | 1  | 1  | 1  | Digit 3           | Starts DTMF dialling of digit |
| x  | x  | 0  | 0  | 1  | 0  | 0  | 1  | Digit 4           | Starts DTMF dialling of digit |
| x  | x  | 0  | 0  | 1  | 0  | 1  | 1  | Digit 5           | Starts DTMF dialling of digit |
| x  | x  | 0  | 0  | 1  | 1  | 0  | 1  | Digit 6           | Starts DTMF dialling of digit |
| x  | x  | 0  | 0  | 1  | 1  | 1  | 1  | Digit 7           | Starts DTMF dialling of digit |
| x  | x  | 0  | 1  | 0  | 0  | 0  | 1  | Digit 8           | Starts DTMF dialling of digit |
| x  | x  | 0  | 1  | 0  | 0  | 1  | 1  | Digit 9           | Starts DTMF dialling of digit |
| x  | x  | 0  | 1  | 0  | 1  | 1  | 1  | Digit *           | Starts DTMF dialling of digit |
| x  | x  | 0  | 0  | 0  | 0  | 0  | 1  | Digit #           | Starts DTMF dialling of digit |
| x  | x  | 0  | 1  | 1  | 0  | 0  | 1  | Digit A           | Starts DTMF dialling of digit |
| x  | x  | 0  | 1  | 1  | 0  | 1  | 1  | Digit B           | Starts DTMF dialling of digit |
| x  | x  | 0  | 1  | 1  | 1  | 0  | 1  | Digit C           | Starts DTMF dialling of digit |
| x  | x  | 0  | 1  | 1  | 1  | 1  | 1  | Digit D           | Starts DTMF dialling of digit |
| x  | x  | 1  | 0  | 0  | 0  | 0  | 1  | KeyReleased       | Stops Dialling                |

| d7 | d6 | d5 | d4 | d3 | d2 | d1 | d0 | Pin-Control message | Notes                        |
|----|----|----|----|----|----|----|----|---------------------|------------------------------|
| x  | x  | 1  | 0  | 1  | 1  | 0  | 1  | SetDPn_HIGH         | Release pin Dpn (open drain) |
| x  | x  | 1  | 0  | 0  | 0  | 1  | 1  | SetDPn_LOW          | Force pin DPn = VSS          |
| x  | x  | 1  | 0  | 0  | 1  | 0  | 1  | SetMask             | Force LI-Voltage to 1.2 V    |
| x  | x  | 1  | 0  | 0  | 1  | 1  | 1  | ResetMask           |                              |

| d7 | d6 | d5 | d4 | d3 | d2 | d1 | d0 | Pin-Control message | Notes                 |
|----|----|----|----|----|----|----|----|---------------------|-----------------------|
| x  | x  | 1  | 0  | 1  | 1  | 1  | 1  | SetTestmode         | FOR FACTORY TEST ONLY |
| x  | x  | 1  | 0  | 1  | 0  | 0  | 1  | MuteON              | Mute Transmit path    |
| x  | x  | 1  | 0  | 1  | 0  | 1  | 1  | MuteOFF             |                       |

| d7 | d6 | d5 | d4 | d3 | d2 | d1 | d0 | Path-Control message | Notes                           |
|----|----|----|----|----|----|----|----|----------------------|---------------------------------|
| x  | x  | 1  | 1  | 0  | 0  | 1  | 1  | SetHandsetPath       |                                 |
| x  | x  | 1  | 1  | 1  | 0  | 1  | 1  | SetMonitorPath       |                                 |
| x  | x  | 1  | 1  | 0  | 1  | 0  | 1  | SetModemPath         |                                 |
| x  | x  | 1  | 1  | 0  | 0  | 0  | 1  | RequestStatus        | AS2540 sends Status information |
| x  | x  | 1  | 1  | 0  | 1  | 1  | 1  | reserved             | <LineEvent>                     |
| x  | x  | 1  | 1  | 1  | 0  | 0  | 1  | reserved             | <LineEvent>                     |
| x  | x  | 1  | 1  | 1  | 1  | 0  | 1  | reserved             | <LineEvent>                     |
| x  | x  | 1  | 1  | 1  | 1  | 1  | 1  | reserved             | <LineEvent>                     |

### Tx messages

<Ack> message

#### <Ack> message format for <RequestStatus>

| b7<br>MSB | b6 | b5 | b4 | b3 | b2 | 0 | 1<br>LSB |
|-----------|----|----|----|----|----|---|----------|
|-----------|----|----|----|----|----|---|----------|

| b7 | b6 | b5 | b4 | b3 | b2 | b1 | b0 | Status                                      | Remark                         |
|----|----|----|----|----|----|----|----|---------------------------------------------|--------------------------------|
| 1  |    |    |    |    |    | 0  | 1  | valid ring signal detected                  | Status of AS2540               |
| 0  |    |    |    |    |    | 0  | 1  | no ring signal                              |                                |
|    | 1  |    |    |    |    | 0  | 1  | manual hook switch - off-hook (pin MHS)     |                                |
|    | 0  |    |    |    |    | 0  | 1  | manual hook switch - on-hook (pin MHS)      |                                |
|    |    | 1  |    |    |    | 0  | 1  | electronic hook switch - off-hook (pin EHS) |                                |
|    |    | 0  |    |    |    | 0  | 1  | electronic hook switch - on-hook (pin EHS)  |                                |
|    |    |    | 0  | 0  | 0  | 0  | 1  | no LLC comparator .....                     | coded status of LLC comparator |
|    |    |    | 0  | 0  | 1  | 0  | 1  | LLC comparator 20mA (45mA) ...              |                                |
|    |    |    | 0  | 1  | 0  | 0  | 1  | LLC comparator 26mA (51mA) ...              |                                |
|    |    |    | 0  | 1  | 1  | 0  | 1  | LLC comparator 32mA (57mA) ...              |                                |
|    |    |    | 1  | 0  | 0  | 0  | 1  | LLC comparator 38mA (63mA) ...              |                                |
|    |    |    | 1  | 0  | 1  | 0  | 1  | LLC comparator 44mA (69mA) ...              |                                |
|    |    |    | 1  | 1  | 0  | 0  | 1  | LLC comparator 50mA (75mA) ...              |                                |



## &lt;Line Event&gt; Message

## &lt;LineEvent&gt; message format

| b7<br>MSB | b6 | b5 | 1 | 1 | 1 | 1 | 1<br>LSB |
|-----------|----|----|---|---|---|---|----------|
|-----------|----|----|---|---|---|---|----------|

| b7 | b6 | b5 | b4 | b3 | b2 | b1 | b0 | Status                                      | Remark           |
|----|----|----|----|----|----|----|----|---------------------------------------------|------------------|
| 1  |    |    | 1  | 1  | 1  | 10 | 1  | valid ring signal detected                  | Status of AS2540 |
| 0  |    |    | 1  | 1  | 1  | 10 | 1  | no ring signal                              |                  |
|    | 1  |    | 1  | 1  | 1  | 10 | 1  | manual hook switch - off-hook (pin MHS)     |                  |
|    | 0  |    | 1  | 1  | 1  | 10 | 1  | manual hook switch - on-hook (pin MHS)      |                  |
|    |    | 1  | 1  | 1  | 1  | 10 | 1  | electronic hook switch - off-hook (pin EHS) |                  |
|    |    | 0  | 1  | 1  | 1  | 10 | 1  | electronic hook switch - on-hook (pin EHS)  |                  |

## Protocol

## Line Events

AS2540 has 3 inputs, namely MHS (Manual Hook Switch), EHS (Electronic Hook Switch) and RFD (Ring Frequency Detector), which sense the state of the two hook-switches and discriminate an applied ring signal. The MHS is connected to the manual hook switch which is operated by the handset and the EHS is connected to an electronic hook switch which is operated by the CPU. Whenever the state of these inputs changes, AS2540 immediately sends <LineEvent> to the CPU after a debounce time. MHS and EHS up-debouncing lasts 15ms, down-debouncing lasts 85ms. RFD start to discriminate the ring frequency immediately but will send a <LineEvent> message with a delay of 102ms. A status change of MHS and EHS pins must not change the momentary selected path of the speech network.

The <LineEvent>-message is sent without consideration of the momentary activities of AS2540 in order to meet PTT requirements (e.g. line break signalling). The code for the <LineEvent>-message is chosen with regard to the minimum current consumption in order to operate the optocouplers. Pending <Ack>-messages will be queued after the <LineEvent>-message. An already running transmissions of <Ack> will not be interrupted and <LineEvent> will be sent afterwards in this case.

## - Mode transitions Idle → BM → MPM → Idle

AS2540 always starts up in backup mode and is prepared to act like an independent dialler. <LineEvent> is sent to the CPU and AS2540 remains in back-up mode until any

valid message is sent from the CPU. This makes sure that a non-operable CPU does not disable basic dialling functions.

## - Mode transition MPM → BM

A watchdog timer is started after <LineEvent> and is reset whenever AS2540 receives a message from the CPU via the serial interface. If the CPU does not send any further valid message within 2400ms, AS2540 goes back into back-up mode, immediately locks the UART and remains in backup mode till next on-hook.

## Dialling Functions

## DTMF

The DTMF generator provides 8 frequencies (in Hz):

|                      |                      |                      |
|----------------------|----------------------|----------------------|
| <b>1</b><br>697+1209 | <b>2</b><br>697+1336 | <b>3</b><br>697+1477 |
| <b>4</b><br>770+1209 | <b>5</b><br>770+1336 | <b>6</b><br>770+1477 |
| <b>7</b><br>852+1209 | <b>8</b><br>852+1336 | <b>9</b><br>852+1477 |
| <b>*</b><br>941+1209 | <b>0</b><br>941+1336 | <b>#</b><br>941+1477 |

The MF output levels are set to -4/-6dB which should allow efficient backup dialling under all line conditions. The TONE/PAUSE ratio is 90ms/90ms. The preemphasis between low group and high group frequencies is t.m. 2.6dB.

### FLASH timing

CPU can control the DPn pin and the MASK-mode of AS2540 via serial interface.

## Tone Ringer

### Ring frequency discrimination

The ring frequency discrimination assures that only signals with a frequency between 13Hz and 70Hz are regarded as valid ring signals.

When a valid ring signal is present for 102ms continuously, the ring melody generator is activated and remains active as long as a valid ring signal is present.

Once the ring melody generator has started, the ring signal is continuously monitored and the ring melody generator is instantly turned off according to the momentary presence of a valid or invalid ring signal until next off-hook.


### Toner ringer melody

The 3 basic melody frequencies are:

- F1=880Hz
- F2=1067Hz
- F3=1333Hz

The repetition rate is set to 4 which means that the sequence of F1, F2, F3, F1, F2, F3 is repeated 4 times within a second.


### Keyboard connections



Double contacts under keys 0-9\*#: One contact is connected to AS2540, the other one to CPU.

## Timing diagrams (unscaled)

### Dialling - MF mode



## Electrical characteristics

Electrical characteristics are measured with the Test Circuit application. Typical mean values will not be tested.

### Absolute maximum ratings

|                                           |                        |
|-------------------------------------------|------------------------|
| Positive Supply Voltage                   | -0.3V ≤ VDD ≤ 7V       |
| Input Current                             | +/- 25mA               |
| Input Voltage (LS)                        | -0.3V ≤ Vin ≤ 10V      |
| Input Voltage (LI, CS)                    | -0.3V ≤ Vin ≤ 8V       |
| Input Voltage (STB, RI)                   | -2V ≤ Vin ≤ VDD+0.3V   |
| Digital Input Voltage                     | -0.3V ≤ Vin ≤ VDD+0.3V |
| Electrostatic Discharge (HBM 1.5kΩ-100pF) | +/- 800V               |
| Storage Temperature                       | -65°C to +125°C        |

### Recommended operating conditions

|                                                          |                 |
|----------------------------------------------------------|-----------------|
| Supply Voltage (generated internally)                    | 3.6V ≤ VDD ≤ 5V |
| Oscillator Frequency<br>Resonator Murata CSA 3.58MG312AM | 3.58MHz         |
| Operating Temperature                                    | -15°C to +60°C  |

### DC characteristics

I<sub>Line</sub>=15mA w/o operation of SI through optocouplers, unless other specified

| Symbol | Parameter                                  | Conditions                       | Min | Typ | Max | Units | Test |
|--------|--------------------------------------------|----------------------------------|-----|-----|-----|-------|------|
| IDD    | Operating Current                          | Speech Mode                      |     | 3   | 5   | mA    | Y    |
|        |                                            | Speech Mode with SI              |     | 5   |     | mA    | N    |
|        |                                            | MF Dialling                      |     | 4   |     | mA    | N    |
|        |                                            | LD Dialling, VDD=2.5V            |     | 200 |     | μA    | N    |
|        |                                            | Ring Mode, VDD=2.5V              |     | 300 |     | μA    | N    |
| VLI    | Line Voltage                               | 15mA ≤ I <sub>LINE</sub> ≤ 100mA | 4.2 | 4.5 | 4.8 | V     | Y    |
| IOL    | Output Current, Sink CS,<br>DPn, MO<br>TXD | VOL=0.4V                         |     | 1   |     | mA    | N    |
|        |                                            | VOL=10mA                         |     | 10  |     | mA    | N    |
| IOH    | Output Current, Source MO                  | VOH=VDD-0.4V                     |     | -1  |     | mA    | N    |

**Transmit characteristics**

| Symbol | Parameter                           | Conditions     | Min   | Typ | Max   | Units | Test |
|--------|-------------------------------------|----------------|-------|-----|-------|-------|------|
| AMTX   | Transmit Gain<br>M1/M2 → LS         | ZAC(syn)=1000Ω | +36.5 | +38 | +39.5 | dB    | Y    |
| ATTX   | Transmit Gain<br>TIT → LS           | ZAC(syn)=1000Ω | +6.5  | +8  | +9.5  | dB    | Y    |
| THD    | Distortion                          | VLS=0.25VRMS   |       |     | 2     | %     | Y    |
| VAGC   | Soft Clip Level<br>M1/M2 → LS at LS |                |       | 2.0 |       | VP    | N    |
| ASCO   | Soft Clip Overdrive<br>M1/M2        |                |       | 20  |       | dB    | N    |
| ZIN    | Input Impedance<br>M1/M2 - TIT      |                |       | 20  |       | kΩ    | N    |
| VNO    | Noise Output Voltage<br>LS          | TAMP=25°C      |       |     | -72   | dBmp  | Y    |
| RL     | Return Loss                         | ZAC(syn)=1000Ω | 18    |     |       | dB    | Y    |

**Receive characteristics**

| Symbol | Parameter                         | Conditions     | Min  | Typ | Max  | Units | Test   |
|--------|-----------------------------------|----------------|------|-----|------|-------|--------|
| AHRX   | Receive Gain<br>LS → ROH          | ZAC(syn)=1000Ω | +0.5 | +2  | +3.5 | dB    | Y      |
| ATRX   | Receive Gain<br>LS → ROT          | ZAC(syn)=1000Ω | -3.5 | -2  | -0.5 | dB    | Y<br>Y |
| THD    | Distortion                        | VLS=0.25VRMS   |      |     | 2    | %     | Y      |
| VAGC   | Soft Clip Level<br>ROH            |                |      | 1   |      | VP    | N      |
| ASCO   | Soft Clip Overdrive<br>ROH        |                |      | 10  |      | dB    | N      |
| VNO    | Noise Output Voltage<br>ROH - ROT | TAMP=25°C      |      |     | -72  | dBmp  | Y      |
| ZIN    | Input Imp. RI                     |                |      | 8   |      | kΩ    | N      |
| ST     | Sidetone                          | VRI≤0.25VRMS   | 24   |     |      | dB    | Y      |
| RL     | Return Loss                       | ZAC(syn)=1000Ω | 18   |     |      | dB    | Y      |

**LD characteristics**

| Symbol | Parameter      | Conditions                                                     | Min | Typ | Max | Units | Test |
|--------|----------------|----------------------------------------------------------------|-----|-----|-----|-------|------|
| t(td)  | Flash Duration | DPN pin status can be directly controlled via serial interface |     |     |     |       |      |

**DTMF characteristics**

| Symbol        | Parameter                     | Conditions      | Min | Typ  | Max | Units | Test |
|---------------|-------------------------------|-----------------|-----|------|-----|-------|------|
| VMFlow        | Tone Level Low Group LS       |                 |     | -6   |     | dBm   | Y    |
| $\Delta$ VL-H | Preemphasis L-H               |                 | 2.0 | 2.6  | 3.2 | dB    | Y    |
| UFC           | Unwanted Frequency Components | 300Hz - 4.3kHz  |     |      | -40 | dBm   | Y    |
|               |                               | 4.3kHz - 7kHz   |     |      | -46 | dBm   | Y    |
|               |                               | 7kHz - 10kHz    |     |      | -52 | dBm   | Y    |
|               |                               | 10kHz - 14kHz   |     |      | -58 | dBm   | Y    |
|               |                               | 14kHz - 28.5kHz |     |      | -70 | dBm   | Y    |
|               |                               | 28.5kHz - 40kHz |     |      | -80 | dBm   | Y    |
| $\Delta$ f    | Frequency Deviation           |                 |     |      | 1.2 | %     | Y    |
| t(td)         | Tone Duration                 |                 | 80  | 82.3 | 85  | ms    | Y    |
| t(itp)        | Inter Tone Pause              |                 | 80  | 82.3 | 85  | ms    | Y    |
| t(mo)         | Mute Overhang                 |                 |     |      | 6   | ms    | Y    |
| VCT-H         | Comfort Tone (DTMF)           | ROH rel. to LS  |     | -30  |     | dB    | N    |

**Ringer characteristics**

| Symbol | Parameter           | Conditions | Min  | Typ  | Max  | Units | Test |
|--------|---------------------|------------|------|------|------|-------|------|
| f1     | Frequency 1         |            | 770  | 800  | 830  | Hz    | Y    |
| f2     | Frequency 2         |            | 1025 | 1067 | 1110 | Hz    | Y    |
| f3     | Frequency 3         |            | 1280 | 1333 | 1385 | Hz    | Y    |
| fMIN   | Min. Det. Frequency |            | 12   | 13   | 14   | Hz    | Y    |
| fMAX   | Max. Det. Frequency |            | 68   | 70   | 75   | Hz    | Y    |
| tDT    | Detection Time      | Initially  |      | 102  |      | ms    | N    |


**Serial Interface**

| Symbol | Parameter                     | Conditions             | Min | Typ   | Max | Units | Test |
|--------|-------------------------------|------------------------|-----|-------|-----|-------|------|
| tRXD-r | RXD signal rise time          | Vdd=4V, RPull-up=1.2kΩ |     | 30    |     | μs    | N    |
| tRXD-f | RXD signal fall time          |                        |     | 30    |     | μs    | N    |
| Vcomp  | Input comparator level at RXD |                        |     | Vdd/2 |     | V     | N    |
| BRRXD  | RXD baud rate                 | +/-2%                  |     | 9600  |     | bps   | N    |
|        |                               |                        |     |       |     |       |      |
| BRTXD  | TXD baud rate                 | +/-2%                  |     | 9600  |     | bps   | Y    |
|        |                               |                        |     |       |     |       |      |
|        |                               |                        |     |       |     |       |      |

**Miscellaneous**


| Symbol    | Parameter        | Conditions | Min | Typ  | Max | Units | Test |
|-----------|------------------|------------|-----|------|-----|-------|------|
| tD        | Key Debouce Time |            |     | 15   |     | ms    | N    |
| ttime-out | Watch-dog Timer  |            |     | 2400 |     | ms    | N    |
|           |                  |            |     |      |     |       |      |

## Typical Application






## Test Circuit



## Packaging

The device is available in the packages outlined below (not to scale). For exact mechanical package dimensions please see austriamicrosystems<sub>AG</sub> packaging information.

28-pin plastic SOIC (suffix T)



|                  |                 |
|------------------|-----------------|
| Max. Body Length | 18.1mm / 713mil |
| Max. Body Width  | 7.6mm / 300mil  |
| Pitch            | 1.27mm / 50mil  |

## Pin-out

|          |           |
|----------|-----------|
| 1 - TIT  | MO - 28   |
| 2 - STB  | TxD - 27  |
| 3 - CS   | RxD - 26  |
| 4 - VSS  | OSC - 25  |
| 5 - LI   | C3 - 24   |
| 6 - RI   | C2 - 23   |
| 7 - LS   | C1 - 22   |
| 8 - CI   | R2 - 21   |
| 9 - ROH  | R1 - 20   |
| 10 - ROT | MODE - 19 |
| 11 - VDD | MHS - 18  |
| 12 - AGD | EHS - 17  |
| 13 - M1  | DPn - 16  |
| 14 - M2  | RFD - 15  |

## Marking

|                                                                                     |                              |
|-------------------------------------------------------------------------------------|------------------------------|
|  | YYWWAAA<br>AS2540<br>Austria |
|-------------------------------------------------------------------------------------|------------------------------|

|     |                               |
|-----|-------------------------------|
| YY  | year of production            |
| WW  | calendar week of production   |
| AAA | ams <sub>AG</sub> assembly ID |

## Ordering Information

| Number  | Package      | Description                                         |
|---------|--------------|-----------------------------------------------------|
| AS2540T | SOIC28       | plastic small outline package - 28 leads (suffix T) |
| AS2540Q | Dice-on-Foil | dice                                                |

Devices sold by austriamicrosystems AG are covered by the warranty and patent identification provisions appearing in its Term of Sale. austriamicrosystems AG makes no warranty, express, statutory, implied, or by description regarding the information set forth herein or regarding the freedom of the described devices from patent infringement. austriamicrosystems AG reserves the right to change specifications and prices at any time and without notice. Therefore, prior to designing this product into a system, it is necessary to check with austriamicrosystems AG for current information. This product is intended for use in normal commercial applications. Applications requiring extended temperature range, unusual environmental requirements, or high reliability applications, such as military, medical life-support or life-sustaining equipment are specifically not recommended without additional processing by austriamicrosystems AG for each application.

## Copyright

Copyright © 1997-2002, austriamicrosystems AG, Schloss Premstaetten, 8141 Unterpremstaetten, Austria-Europe. Trademarks Registered ®. All rights reserved. The material herein may not be reproduced, adapted, merged, translated, stored, or used without the prior written consent of the copyright owner.

The information furnished here by austriamicrosystems AG is believed to be correct and accurate. However, austriamicrosystems AG shall not be liable to recipient or any third party for any damages, including but not limited to personal injury, property damage, loss of profits, loss of use, interruption of business or indirect, special, incidental or consequential damages, of any kind, in connection with or arising out of the furnishing, performance or use of the technical data herein. No obligation or liability to recipient or any third party shall arise or flow out of austriamicrosystems AG rendering of technical or other services.

## Contact

### Headquarters

austriamicrosystems AG  
Communications Business Unit  
A 8141 Schloss Premstätten, Austria  
T. +43 (0) 3136 500 0  
F. +43 (0) 3136 525 01  
[www.austriamicrosystems.com](http://www.austriamicrosystems.com)

## Sales Offices

### Germany

austriamicrosystems Germany GmbH  
Tegernseer Landstrasse 85  
D-81539 München, Germany  
Phone: +49/89/693643-0  
Fax: +49/89/693643-66

### France

austriamicrosystems France S.a.r.l.  
124, Avenue de Paris  
F-94300 Vincennes, France  
Phone: +33/1/43 74 00 90  
Fax: +33/1/43 74 20 98

### Italy

austriamicrosystems Italy S.r.l.  
Via Leone Tolstoi, 64  
I-20146 Milano, Italy  
Phone: +39/0242/36713  
Fax: +39/0242/290889

### Switzerland

austriamicrosystems Switzerland AG  
Rietstrasse 4  
CH-8640 Rapperswil, Switzerland  
Phone: +41/55/220 9000  
Fax: +41/55/220 9001

### USA (west)

austriamicrosystems USA, Inc.  
Suite 116, 4030 Moorpark Ave,  
San Jose, CA 95117, USA  
Phone: +1/408/345 1790  
Fax: +1/408/345 1795

### USA (east)

austriamicrosystems USA, Inc.  
Suite 400, 8601 Six Forks Road  
Raleigh, NC 27615, USA  
Phone: +1/919/676 5292  
Fax: +1/919/676 5305

### United Kingdom

austriamicrosystems UK, Ltd.  
Coliseum Business Centre, Watchmoor Park  
Camberley, Surrey, GU15 3YL, UK  
Phone: +44/1276/23 3 99  
Fax: +44/1276/29 3 53

### Japan

austriamicrosystems AG  
Shin Yokohama Daini, Center Bldg. 10F  
3-19-5, Shin Yokohama  
Kohoku-ku, Yokohama 222-0033, Japan  
Phone: +81/45/474 0962  
Fax: +81/45/472 9845

## Distributors & Representatives

austriamicrosystems AG is represented by distributors in the following countries. Please contact your nearest regional sales office for the distributor address:

Spain, Israel, Korea, Hong-Kong, Taiwan, Malaysia, Singapore, India, Brazil

## Application Support

Please contact your local sales office or your distributor.

# AMEYA360

Components Supply Platform

Authorized Distribution Brand :



Website :

Welcome to visit [www.ameya360.com](http://www.ameya360.com)

Contact Us :

➤ Address :

401 Building No.5, JiuGe Business Center, Lane 2301, Yishan Rd  
Minhang District, Shanghai , China

➤ Sales :

Direct     +86 (21) 6401-6692  
Email      amall@ameya360.com  
QQ         800077892  
Skype      ameyasales1 ameyasales2

➤ Customer Service :

Email      service@ameya360.com

➤ Partnership :

Tel         +86 (21) 64016692-8333  
Email      mkt@ameya360.com