











MOTOR CIRCUIT

120V, 50/60 HZ

* ROTATION AS VIEWED
FROM MOTOR END

MOTOR SPEED: SEE CHART

++ LINE TO LINE VOLTAGE

- + MOTOR DRIVEN UNITS USE TERMINAL CONNECTIONS FOR CCW INCREASING VOLTAGE, AS VIEWED FROM BASE END.
- THE GANGED UNITS ARE USED IN A SYSTEM THAT ORDINARILY HAS A COMMON NEUTRAL OR GROUND BETWEEN SOURCE AND LOAD, THE NEUTRAL OR GROUND MUST BE CONNECTED TO THE COMMON TERMINALS OF THE VARIABLE TRANSFORMER ASSEMBLY. IF THE SYSTEM HAS NO NEUTRAL, THE LOAD MUST BE BALANCED OR THE TRANSFORMERS WILL BE DAMAGED.
- JUMPER PROVIDED IN THE STANDARD COMMON POSITION AND SHOULD BE MOVED OR REMOVED AS REQUIRED.

SPECIFICATIONS											
	INPUT		OUTPUT					SHAFT	TERMINAL CONNECTIONS		
WIRING	VOLTS	HERTZ	VOLTS	CONSTANT CURRENT LOAD		CONSTANT IMPEDANCE LOAD		ROTATION TO INCREASE	FOR INCREASING VOLTAGE AS VIEWED FROM BASE END +		
				MAX. AMPS	MAX. KVA	MAX. AMPS	MAX. KVA	VOLTAGE	INPUT		
THREE		/		4.0		4.7		CW	1-1-1	4-4-4	3-3-3
PHASE	240	50/60	0-240	10	4.16	13	5.4	CCW	4-4-4	1-1-1	3-3-3
WYE	++		0-280	4.0	4.85			CW	5-5-5	4-4-4	3-3-3
π		60	0-280	10	4.05			CCW	2-2-2	1-1-1	3-3-3
UNLESS OTHERWISE SPECIFIED. TOLERANCE IS ± DECIMALS HOLES ANGLES DRAFT			UNITS	TITLE: SPFC		001	JTRO	I DRAV	NING		7

SPEED MODEL (SECONDS) NUMBER 5 5M1010B-3 20.25 [514.2] 15 15M1010B-3 20.25 [514.2] 30 30M1010B-3 20.64 [524.2] 60 60M1010B-3 20.64 [524.2]

ANGLES DRATT IN [1-1/2*] IN [1



Authorized Distribution Brand:

























Website:

Welcome to visit www.ameya360.com

Contact Us:

Address:

401 Building No.5, JiuGe Business Center, Lane 2301, Yishan Rd Minhang District, Shanghai , China

Sales :

Direct +86 (21) 6401-6692

Email amall@ameya360.com

QQ 800077892

Skype ameyasales1 ameyasales2

Customer Service :

Email service@ameya360.com

Partnership :

Tel +86 (21) 64016692-8333

Email mkt@ameya360.com