

JTAGjet™ - Trace for Cortex-M series with Real-Time ETM Trace

JTAGjet-Trace-CM is a small, palm-sized In-Circuit Debugger (commonly called emulator) used for debugging, testing and verification of embedded systems based on the Cortex-M devices. It is equipped with ETM trace memory that captures the compressed data on the ETM port in real-time so it can be decompressed, decoded and displayed on the PC showing the program execution path and variable changes.

Complete ARM Core Support

JTAGjet-Trace supports all **Cortex-M** based devices, however, the trace capability can be only used on devices with the ETM port.

Chameleon Debugger™

Each emulator is bundled with a Chameleon Debugger™, a high-end, full-featured, **multi-core debugger** that handles single and multi-CPU debugging. Chameleon Debugger features macros for automated board initialization and testing, fly-over variable pop-ups in source window, drag-and-drop between windows, Graphical Event Triggering and hundreds of other time saving debug features.

Keil uVision™ Support

JTAGjet-Trace-CM is compatible with Keil uVision debugger making it an ideal complementing tool to their IDE, simulator and code generation tools.

Multi-Core Debugging

One of the unique JTAGjet features is that it may be used concurrently with other debuggers (like TI Code Composer Studio or eSOL eBinder), offering a complete multi-core debug environment.

Smart Flash Programmer

JTAGjet comes with a Flash Programmer that recognizes the type and geometry of the device and automatically configures the flashing algorithm. Both on-chip and external NOR flash devices are supported. NAND flash programming is available as an external utility option.

Adaptive JTAG Clock & Voltage

JTAGjet-Trace supports fixed and adaptive JTAG clocks. Adaptive clock is synchronized with the CPU and is recommended on systems that vary the CPU clock to conserve power.

The emulator automatically adjusts the JTAG output signals to the VTREF voltage on the target board and supports 1.8V to 3.3V targets.



JTAGjet-Trace-CM Features

- ☐ Trace capture of up to the **maximum CPU speed**
- ☐ Supports Cortex-M0, M1, M3, M4 cores equipped with Embedded Trace Macrocell (**ETM**) from Atmel, Freescale, NXP, ST Micro, TI, Toshiba and others.
- ☐ **Keil uVision** compatible
- ☐ **Upgradeable** to support other ARM cores: ARM7, ARM9, ARM11, Cortex-R, Cortex-A, OMAP, DaVinci, Sitara, etc.
- ☐ Auto **adjusting timing** eliminates problems with data skew
- ☐ **4.5 MBytes** of internal ETM trace memory, upgradeable to 18 MBytes to capture longer execution times
- ☐ 56-bit time stamp with CPU cycle accuracy for **timing analysis**
- ☐ Easy access to ETM settings, triggers and trace filtering
- ☐ Quiet operation – no fans, no external heat sinks
- ☐ Only one connection to target – both JTAG and trace are taken from a high-density, 20-pin Cortex header.
- ☐ Optional Mictor-38 ETM cable and plain JTAG adapter

Chameleon Debugger™ Features:

- ☐ Non-intrusive **ETM & ETB trace** display and debugging
- ☐ **Synchronized** Source and Trace windows for easy debugging
- ☐ Pre- and post-capture **filtering of trace** data
- ☐ Trace clock (CPU speed) display in real-time
- ☐ Instrumentation Trace (**ITM**) display
- ☐ Support for all on-chip breakpoints, triggers and filtering
- ☐ Super fast code downloads
- ☐ JTAG and **Serial Wire Debug** (SWD) support
- ☐ Support for all three CPU resets: **Core, System and Hardware Reset**
- ☐ Automatic **processor initialization** on power-up or reset (memory mapping, peripheral setting, MMU, WD disable etc.)
- ☐ **Flash Programming** from GUI or from macros (DOS batch mode utility is also available)
- ☐ **Multi-Core** support for debugging of two or more devices on the same JTAG or separate JTAG connection
- ☐ Available **Concurrent Debugging** to allow two different debuggers to access two different cores at the same time
- ☐ Windows XP & Vista 32 & 64-bit compatible

Specifications

JTAGjet-Trace-CM

Specifications	JTAGjet-Trace-CM
USB type / Speed	USB 2.0 type A / 480 Mbps
ETM Trace Memory	4.5 MBytes standard, 18Mbytes optional
Cores Supported	Cortex-M0, M1, M3, M4, upgradeable to other ARM cores
Max. ETM Trace Clock	200 MHz
Max. JTAG Clock	30 MHz
Probe Length	4 in
Probe Type	20-pin Cortex/SWD standard, Mictor-38 optional
JTAG I/O Voltage	1.8V – 3.3V
Current Draw (typ.)	0.8A typ., AC adapter included
Dimensions (in.)	5.6L-2.6W-1.2H



JTAGjet-Trace-CM shown with optional blue Mictor-38 cable and JTAG splitter (green)

CortexM3:trace

#	PC	Disas	Source	TStamp [abs]...	TStamp [rel]...	RdWr	ITMPar	MemData
#61	processing+0x2	LDRB R1,[R0,#0]	if (*text != ' '){...	0.001	-12794			
#61/1	processing+0x4	CMP R1,#0x20		0.001	-12793			
#61/2	processing+0x6	[--]BEQ 0x20000076		0.001	-12792			
#67	processing+0x8	LDRSB R1,[R0,#+0]	*text ^= 0x20; ...	0.001	-12788			
#67/1	processing+0xC	EOR R1,R1,#0x20		0.001	-12787			
#67/2	processing+0x10	STRE R1,[R0,#0]		0.001	-12786			
#69				0.001	-12786	Rd	Comp1	0x67
#73				0.001	-12782	Rd	Comp1	0x67
#77				0.001	-12778	Wr	Comp1	0x47
#132	processing	B 0x20000078	while (*text != '\0')...	0.179	0			
#136	processing+0x14	LDRB R1,[R0,#0]	while (*text != '\0')...	0.179	4			
#136/1	processing+0x16	CMP R1,#0		0.179	5			
#136/2	processing+0x18	BNE 0x20000066		0.179	6			
#140	processing+0x2	LDRB R1,[R0,#0]	if (*text != ' '){...	0.179	8			
#140/1	processing+0x4	CMP R1,#0x20		0.179	9			
#140/2	processing+0x6	[--]BEQ 0x20000076		0.179	10			
#144					12	Rd	Comp0	0x53
#150					18	Rd	Comp0	0x53
#154					22	Rd	Comp0	0x53
#158					26	Wr	Comp0	0x73
#162					30	Rd	Comp1	0x47
#166					34	Rd	Comp1	0x47
#170					38	Rd	Comp1	0x47
#176					44			
#176/1	process				45			
#176/2	process				46			
#176/3	process				47			
#176/4	process				48			
#176/5	process				49			
#176/6	process				50			
#182	process				50			
#182/1	process				51			
#182/2	process				52			
#184	process				52			

Trace Clock: 36.00MHz

CortexM3:setup

Comparator0: Output, Function, Access, Value, Ignore Bits

ITM Trace, Emit Data on Data Address Match, Read or Write, &Buf1[0]

Comparator1: Output, Function, Access, Value, Ignore Bits

ITM Trace, Emit Data on Data Address Match, Read or Write, &Buf1[2]

Address Match 0, Address Match 1, Data Value Size

Data Address Range: None, None, Word

Comparator2: Output, Function, Access, Value, Ignore Bits

ETM Event, PC Match, Fetch, processing

Comparator3: Output, Function, Access, Value, Ignore Bits

ETM Event, Data Address Match, Write, &Buf1[2]

Status: NotActive

Trace window showing real-time trace information captured during program execution. Full program path (PC) is shown with function names and the corresponding assembler and C/C++ source code. In addition, on-chip Comparators (shown in the **setup** window) were set to generate **ITM data trace** for **Buf1[0]** and **Buf1[2]** accesses. Comparator2 is used to generate **ETM Event** to start the trace on **processing** function and Comparator3 is used to stop the trace on **write to location Buf1[2]**. Red line shows trace discontinuity. Yellow line shows STRE instruction (which was a write of 0x47 to Buf1[2] that stopped the PC trace). **Timestamp** is being shown in two columns (in ms and CPU cycles). The gap in trace capture was for 12778 CPU cycles (~178 ms).

Current Trace Clock frequency is shown as **36MHz**. Cortex-M CPU always runs twice as fast as the Trace Clock, so the CPU speed is **72 MHz**.

Ordering Information

Part Number	Description	Price
JTAGjet-Trace-CM	JTAGjet for Cortex-M with 4.5 MBytes ETM trace memory, Chameleon Debugger, Keil uV driver and Cortex 20-pin cable	\$ 1,995
JTAGjet-Trace-CM2	JTAGjet for Cortex-M with 4.5 MBytes ETM trace memory, Chameleon Debugger, Keil uV driver and Cortex 20-pin cable	\$ 2,500
JTAGjet-Trace-CM4	JTAGjet for Cortex-M with 4.5 MBytes ETM trace memory, Chameleon Debugger, Keil uV driver and Cortex 20-pin cable	\$ 3,000
Cable-ETM-6	Mictor 38-pin ETM cable, 6 inch (optional)	\$ 250
ADA-ETM-JTAG	Mictor 38-pin ETM to ARM-20 and TI-14 splitter probe. Comes with 20-pin and 14-pin flat cables (optional)	\$ 250
MDK-ARM-B	Keil IDE with RealView compile tools (256K limited) for ARM7, ARM9 and Cortex-M, uVision debugger and simulator	\$ 2,895
MDK-ARM	Keil IDE with RealView compile tools (unlimited) for ARM7, ARM9 and Cortex-M, uVision debugger and simulator	\$ 4,895



1211 Flynn Rd., Unit 104, Camarillo, CA 93012
Phone: (805) 383-3682
Fax: (805) 383-3685

Toll Free: 1 • 800 • 838 • 8012
Email: sales@signum.com
Web: www.signum.com

AMEYA360

Components Supply Platform

Authorized Distribution Brand :



Website :

Welcome to visit www.ameya360.com

Contact Us :

➤ Address :

401 Building No.5, JiuGe Business Center, Lane 2301, Yishan Rd
Minhang District, Shanghai , China

➤ Sales :

Direct +86 (21) 6401-6692

Email amall@ameya360.com

QQ 800077892

Skype ameyasales1 ameyasales2

➤ Customer Service :

Email service@ameya360.com

➤ Partnership :

Tel +86 (21) 64016692-8333

Email mkt@ameya360.com