

120-V Boot, 3-A Peak, High Frequency, High-Side/Low-Side Driver

Check for Samples: [UCC27200A](#), [UCC27201A](#)

FEATURES

- Specified from -40 °C to 140 °C
- Drives Two N-Channel MOSFETs in High-Side/Low-Side Configuration
- Maximum Boot Voltage 120 V
- Maximum VDD Voltage 20 V
- On-Chip 0.65-V VF, 0.6-Ω RD Bootstrap Diode
- Greater than 1 MHz of Operation
- 20-ns Propagation Delay Times
- 3-A Sink, 3-A Source Output Currents
- 8-ns Rise/7-ns Fall Time with 1000-pF Load
- 1-ns Delay Matching
- Under Voltage Lockout for High-Side and Low-Side Driver
- Offered in 8-Pin SOIC (D), PowerPad™ SOIC-8 (DDA), SON-8 (DRM), SON-9 (DRC) and SON-10 (DPR) Packages

APPLICATIONS

- Power Supplies for Telecom, Datacom, and Merchant Markets
- Half-Bridge Applications and Full-Bridge Converters
- Isolated Bus Architecture
- Two-Switch Forward Converters
- Active-Clamp Forward Converters
- High Voltage Synchronous-Buck Converters
- Class-D Audio Amplifiers


CONTENTS

| | |
|--|----|
| Device Ratings | 2 |
| Electrical Characteristics | 4 |
| Device Information | 11 |
| Application Information | 14 |
| Additional References | 22 |

DESCRIPTION

The UCC27200A/1A family of high frequency N-Channel MOSFET drivers include a 120-V bootstrap diode and high-side/low-side driver with independent inputs for maximum control flexibility. This allows for N-Channel MOSFET control in half-bridge, full-bridge, two-switch forward and active clamp forward converters. The low-side and the high-side gate drivers are independently controlled and matched to 1-ns between the turn-on and turn-off of each other. The UCC27200A/1A are based on the popular UCC27200/1 drivers, but offer some enhancements. In order to improve performance in noisy power supply environments the UCC27200A/1A has an enhanced ESD input structure and also has the ability to withstand a maximum of -18 V on its HS pin.

Simplified Application Diagram



Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.

PowerPad is a trademark of Texas Instruments.

PRODUCTION DATA information is current as of publication date. Products conform to specifications per the terms of the Texas Instruments standard warranty. Production processing does not necessarily include testing of all parameters.

Copyright © 2011, Texas Instruments Incorporated



These devices have limited built-in ESD protection. The leads should be shorted together or the device placed in conductive foam during storage or handling to prevent electrostatic damage to the MOS gates.

DESCRIPTION (CONT.)

An on-chip bootstrap diode eliminates the external discrete diodes. Under-voltage lockout is provided for both the high-side and the low-side drivers forcing the outputs low if the drive voltage is below the specified threshold.

Two versions of the UCC27200A are offered. The UCC27200A has high noise immune CMOS input thresholds while the UCC27201A has TTL compatible thresholds.

Both devices are offered in an 8-pin SOIC(D), PowerPad™ SOIC-8(DDA), SON-8(DRM) package, a 9-pin SON-9(DRC) package and a 10-pin SON-10(DPR) package.

ORDERING INFORMATION

| PACKAGED DEVICES ⁽¹⁾ | | | | | | |
|---------------------------------|---------------------|---------------------------|---------------------------------------|----------------------------|----------------------------|-----------------------------|
| TEMPERATURE RANGE $T_A = T_J$ | INPUT COMPATIBILITY | SOIC-8 (D) ⁽²⁾ | PowerPad™ SOIC-8 (DDA) ⁽²⁾ | SON-8 (DRM) ⁽³⁾ | SON-9 (DRC) ⁽⁴⁾ | SON-10 (DPR) ⁽⁵⁾ |
| -40°C to +140°C | CMOS | UCC27200AD | UCC27200ADDA | UCC27200ADRM | UCC27200ADRC | N/A |
| | TTL | UCC27201AD | UCC27201ADDA | UCC27201ADRM | UCC27201ADRC | UCC27201ADPR |

- (1) These products are packaged in Lead (Pb)-Free and green lead finish of PdNiAu which is compatible with MSL level 1 at 255-260°C peak reflow temperature to be compatible with either lead free or Sn/Pb soldering operations.
- (2) D (SOIC-8) and DDA (Power Pad™ SOIC-8) packages are available taped and reeled. Add R suffix to device type (e.g. UCC27200ADR) to order quantities of 2,500 devices per reel.
- (3) DRM (SON-8) package comes either in a small reel of 250 pieces as part number UCC27200ADRM, or larger reels of 3000 pieces as part number UCC27200ADRM.
- (4) DRC(SON-9) package comes either in a small reel of 250 pieces as part number UCC27200ADRCT, or large reels pieces as part number UCC27200ADRRC.
- (5) DPR(SON-10) package comes either in a small reel of 250 pieces as part number UCC27201ADPRT, or large reels pieces as part number UCC27201ADPRR.

DEVICE RATINGS

ABSOLUTE MAXIMUM RATINGS

Over operating free-air temperature, unless noted, all voltages are with respect to V_{SS} ⁽¹⁾

| PARAMETER | | VALUE | UNIT |
|--|---|---|------|
| Supply voltage range, ⁽²⁾ V_{DD} | | -0.3 to 20 | V |
| Input voltages on LI and HI, V_{LI} , V_{HI} | | -0.3 to 20 | |
| Output voltage on LO, V_{LO} | DC | -0.3 to $V_{DD} + 0.3$, | |
| | Repetitive pulse <100 ns ⁽³⁾ | -2 to $V_{DD} + 0.3$ | |
| Output voltage on HO, V_{HO} | DC | $V_{HS} - 0.3$ to $V_{HB} + 0.3$ | |
| | Repetitive pulse <100 ns ⁽³⁾ | $V_{HS} - 2$ to $V_{HB} + 0.3$, ($V_{HB} - V_{HS} < 20$) | |
| Voltage on HS, V_{HS} | DC | -1 to 120 | |
| | Repetitive pulse <100 ns ⁽³⁾ | -18 to 120 | |
| Voltage on HB, V_{HB} | | -0.3 to 120 | |
| Voltage On HB-HS | | -0.3 to 20 | |
| Operating virtual junction temperature range, T_J | | -40 to +150 | °C |
| Storage temperature, T_{STG} | | -65 to +150 | |
| Lead temperature (soldering, 10 sec.) | | +300 | |
| Power dissipation at $T_A = 25^\circ\text{C}$ (D package) ⁽⁴⁾ | | 1.3 | W |
| Power dissipation at $T_A = 25^\circ\text{C}$ (DDA package) ⁽⁴⁾ | | 2.7 | |
| Power dissipation at $T_A = 25^\circ\text{C}$ (DRM package) ⁽⁴⁾ | | 3.3 | |
| Power dissipation at $T_A = 25^\circ\text{C}$ (DRC package) ⁽⁴⁾ | | 2.86 | |
| Human body model | | 2000 | V |
| CDM | | 1000 | |

- (1) Stresses beyond those listed under “absolute maximum ratings” may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under “recommended operating conditions” is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.
- (2) All voltages are with respect to V_{SS} . Currents are positive into, negative out of the specified terminal.
- (3) Values are verified by characterization and are not production tested.
- (4) This data was taken using the JEDEC proposed high-K test PCB. See the THERMAL CHARACTERISTICS section for details.

RECOMMENDED OPERATING CONDITIONS

over operating free-air temperature range (unless otherwise noted)

| PARAMETER | | MIN | NOM | MAX | UNIT |
|-----------|---|--------------------------------|-----|------------------------|--------|
| V_{DD} | Supply voltage range | 8 | 12 | 17 | V |
| V_{HS} | Voltage on HS | -1 | | 105 | |
| | Voltage on HS, (repetitive pulse <100 ns) | -15 | | 110 | |
| V_{HB} | Voltage on HB | $V_{HS} + 8$, $V_{DD} - 1$ | | $V_{HS} + 17$, 115 | |
| | Voltage slew rate on HS | | | 50 | V / ns |
| T_J | Operating junction temperature range | -40 | | +140 | °C |

THERMAL INFORMATION

| THERMAL METRIC ⁽¹⁾ (2) | | UCC27200A /UCC27201A | UCC27200A /UCC27201A | UCC27200A /UCC27201A | UNITS |
|-----------------------------------|--|-------------------------|-------------------------|-------------------------|-------|
| | | DRM | DRC | DPR | |
| | | 8 PINS | 9 PINS | 10 PINS | |
| θ_{JA} | Junction-to-ambient thermal resistance | 36.2 | 43.7 | 34.8 | °C/W |
| θ_{JCTop} | Junction-to-case (top) thermal resistance | 41.6 | 49.9 | 32.1 | |
| θ_{JB} | Junction-to-board thermal resistance | 13.2 | 19.1 | 11.9 | |
| Ψ_{JT} | Junction-to-top characterization parameter | 0.6 | 0.6 | 0.2 | |
| Ψ_{JB} | Junction-to-board characterization parameter | 13.4 | 19.3 | 12.2 | |
| θ_{JCbott} | Junction-to-case (bottom) thermal resistance | 3.1 | 3.8 | 1.3 | |

(1) For more information about traditional and new thermal metrics, see the *IC Package Thermal Metrics* application report, [SPRA953](#).

(2) For thermal estimates of this device based on PCB copper area, see the [TI PCB Thermal Calculator](#).

THERMAL INFORMATION

| THERMAL METRIC ⁽¹⁾ (2) | | UCC27200A /UCC27201A | UCC27200A /UCC27201A | UNITS |
|-----------------------------------|--|-------------------------|-------------------------|-------|
| | | D | DDA | |
| | | 8 PINS | 8 PINS | |
| θ_{JA} | Junction-to-ambient thermal resistance | 106.5 | 40.5 | °C/W |
| θ_{JCTop} | Junction-to-case (top) thermal resistance | 52.9 | 49.0 | |
| θ_{JB} | Junction-to-board thermal resistance | 46.6 | 10.2 | |
| Ψ_{JT} | Junction-to-top characterization parameter | 9.6 | 3.1 | |
| Ψ_{JB} | Junction-to-board characterization parameter | 46.1 | 9.7 | |
| θ_{JCbott} | Junction-to-case (bottom) thermal resistance | n/a | 1.5 | |

(1) For more information about traditional and new thermal metrics, see the *IC Package Thermal Metrics* application report, [SPRA953](#).

(2) For thermal estimates of this device based on PCB copper area, see the [TI PCB Thermal Calculator](#).

ELECTRICAL CHARACTERISTICS

over operating free-air temperature range, $V_{DD} = V_{HB} = 12\text{ V}$, $V_{HS} = V_{SS} = 0\text{ V}$, No load on LO or HO, $T_A = T_J = -40^\circ\text{C}$ to $+140^\circ\text{C}$, (unless otherwise noted)

| PARAMETER | | | TEST CONDITIONS | | MIN | TYP | MAX | UNIT |
|--------------------------------|---|-------------------------------|---|--|-----|--------|------|------|
| Supply Currents | | | | | | | | |
| I _{DD} | VDD quiescent current | | V _{LI} = V _{HI} = 0 | | | 0.4 | 0.8 | mA |
| I _{DDO} | VDD operating current | UCC27200A | f = 500 kHz, C _{LOAD} = 0 | | | 2.5 | 4 | |
| | | UCC27201A | f = 500 kHz, C _{LOAD} = 0 | | | 3.8 | 5.5 | |
| I _{HB} | Boot voltage quiescent current | | V _{LI} = V _{HI} = 0 V | | | 0.4 | 0.8 | |
| I _{HBO} | Boot voltage operating current | | f = 500 kHz, C _{LOAD} = 0 | | | 2.5 | 4 | |
| I _{HBS} | HB to V _{SS} quiescent current | | V _{HS} = V _{HB} = 110 V | | | 0.0005 | 1 | uA |
| I _{HBSO} | HB to V _{SS} operating current | | f = 500 kHz, C _{LOAD} = 0 | | | 0.1 | | mA |
| Input | | | | | | | | |
| V _{HIT} | Input rising threshold | | UCC27200A | | | 5.8 | 8 | V |
| V _{LIT} | Input falling threshold | | | | 3 | 5.4 | | |
| V _{IHYS} | Input voltage hysteresis | | | | | 0.4 | | |
| V _{HIT} | Input voltage threshold | | UCC27201A | | | 1.7 | 2.5 | |
| V _{LIT} | Input voltage threshold | | | | 0.8 | 1.6 | | |
| V _{IHYS} | Input voltage Hysteresis | | | | | 100 | | mV |
| R _{IN} | Input pulldown resistance | | | | 100 | 200 | 350 | kΩ |
| Undervoltage Protection (UVLO) | | | | | | | | |
| | VDD rising threshold | | | | 6.2 | 7.1 | 7.8 | V |
| | VDD threshold hysteresis | | | | | 0.5 | | |
| | VHB rising threshold | | | | 5.8 | 6.7 | 7.2 | |
| | VHB threshold hysteresis | | | | | 0.4 | | |
| Bootstrap Diode | | | | | | | | |
| V _F | Low-current forward voltage | | I _{VDD} - HB = 100 μA | | | 0.65 | 0.85 | V |
| V _{FI} | High-current forward voltage | | I _{VDD} - HB = 100 mA | | | 0.85 | 1.1 | |
| R _D | Dynamic resistance, ΔVf/ΔI | | I _{VDD} - HB = 100 mA and 80 mA | | | 0.6 | 1.0 | Ω |
| LO Gate Driver | | | | | | | | |
| V _{LOL} | Low level output voltage | | I _{LO} = 100 mA | | | 0.18 | 0.4 | V |
| V _{LOH} | High level output voltage | T _J = -40 to 125°C | I _{LO} = -100 mA, V _{LOH} = V _{DD} - V _{LO} | | | 0.25 | 0.4 | |
| | | T _J = -40 to 140°C | I _{LO} = -100 mA, V _{LOH} = V _{DD} - V _{LO} | | | 0.25 | 0.42 | |
| | Peak pull-up current | | V _{LO} = 0 V | | | 3 | | |
| | Peak pull-down current | | V _{LO} = 12 V | | | 3 | | |
| HO Gate Driver | | | | | | | | |
| V _{HOL} | Low level output voltage | | I _{HO} = 100 mA | | | 0.18 | 0.4 | V |
| V _{HOH} | High level output voltage | T _J = -40 to 125°C | I _{HO} = -100 mA, V _{HOH} = V _{HB} -V _{HO} | | | 0.25 | 0.4 | |
| | | T _J = -40 to 140°C | I _{HO} = -100 mA, V _{HOH} = V _{HB} -V _{HO} | | | 0.25 | 0.42 | |
| | Peak pull-up current | | V _{HO} = 0 V | | | 3 | | |
| | Peak pull-down current | | V _{HO} = 12 V | | | 3 | | |
| Propagation Delays | | | | | | | | |

ELECTRICAL CHARACTERISTICS (continued)






over operating free-air temperature range, $V_{DD} = V_{HB} = 12\text{ V}$, $V_{HS} = V_{SS} = 0\text{ V}$, No load on LO or HO, $T_A = T_J = -40^\circ\text{C}$ to $+140^\circ\text{C}$, (unless otherwise noted)

| PARAMETER | | TEST CONDITIONS | | MIN | TYP | MAX | UNIT |
|---------------------------|--|---|-----------------------|-----|------|-----|------|
| t _{DLFF} | V _{LI} falling to V _{LO} falling | T _J = -40 to 125°C | C _{LOAD} = 0 | | 20 | 45 | ns |
| | | T _J = -40 to 140°C | C _{LOAD} = 0 | | 20 | 50 | |
| t _{DHFF} | V _{HI} falling to V _{HO} falling | T _J = -40 to 125°C | C _{LOAD} = 0 | | 20 | 45 | |
| | | T _J = -40 to 140°C | C _{LOAD} = 0 | | 20 | 50 | |
| t _{DLRR} | V _{LI} rising to V _{LO} rising | T _J = -40 to 125°C | C _{LOAD} = 0 | | 20 | 45 | |
| | | T _J = -40 to 140°C | C _{LOAD} = 0 | | 20 | 50 | |
| t _{DHRR} | V _{HI} rising to V _{HO} rising | T _J = -40 to 125°C | C _{LOAD} = 0 | | 20 | 45 | |
| | | T _J = -40 to 140°C | C _{LOAD} = 0 | | 20 | 50 | |
| Delay Matching | | | | | | | |
| t _{MON} | LI ON, HI OFF | | | | 1 | 7 | ns |
| t _{MOFF} | LI OFF, HI ON | | | | 1 | 7 | |
| Output Rise and Fall Time | | | | | | | |
| t _R | LO, HO | C _{LOAD} = 1000 pF | | | 8 | | ns |
| t _F | LO, HO | C _{LOAD} = 1000 pF | | | 7 | | |
| t _R | LO, HO (3 V to 9 V) | C _{LOAD} = 0.1 μF | | | 0.35 | 0.6 | us |
| t _F | LO, HO (3 V to 9 V) | C _{LOAD} = 0.1 μF | | | 0.3 | 0.6 | |
| Miscellaneous | | | | | | | |
| | Minimum input pulse width that changes the output | | | | 50 | | ns |
| | Bootstrap diode turn-off time | I _F = 20 mA, I _{REV} = 0.5 A ^{(1) (2)} | | | 20 | | |

(1) Typical values for $T_A = 25^\circ\text{C}$

(2) I_F : Forward current applied to bootstrap diode, I_{REV} : Reverse current applied to bootstrap diode.

DEVICE INFORMATION



NOTE

Pin VSS and the exposed thermal die pad are internally connected.

PIN FUNCTIONS

| PIN | | | | I/O | DESCRIPTION |
|-----------|--------------------|-----|-----|-----|---|
| PIN NAME | DRM/D/DDA | DRC | DPR | | |
| VDD | 1 | 1 | 1 | I | Positive supply to the lower gate driver. De-couple this pin to VSS (GND). Typical decoupling capacitor range is 0.22 μ F to 1.0 μ F. |
| HB | 2 | 2 | 2 | I | High-side bootstrap supply. The bootstrap diode is on-chip but the external bootstrap capacitor is required. Connect positive side of the bootstrap capacitor to this pin. Typical range of HB bypass capacitor is 0.022 μ F to 0.1 μ F, the value is dependant on the gate charge of the high-side MOSFET however. |
| HO | 3 | 3 | 3 | O | High-side output. Connect to the gate of the high-side power MOSFET. |
| HS | 4 | 4 | 4 | I | High-side source connection. Connect to source of high-side power MOSFET. Connect negative side of bootstrap capacitor to this pin. |
| HI | 5 | 6 | 7 | I | High-side input. |
| LI | 6 | 7 | 8 | I | Low-side input. |
| VSS | 7 | 8 | 9 | O | Negative supply terminal for the device which is generally grounded. |
| LO | 8 | 9 | 10 | O | Low-side output. Connect to the gate of the low-side power MOSFET. |
| N/C | - | 5 | 5/6 | - | No connection. Pins labeled N/C have no connection. |
| PowerPAD™ | Pad ⁽¹⁾ | Pad | Pad | - | Connect to a large thermal mass trace or GND plane to dramatically improve thermal performance. |

- (1) Pin VSS and the exposed thermal die pad are internally connected on the DDA and DRM packages only. Electrically referenced to VSS (GND).

FUNCTIONAL BLOCK DIAGRAM




Figure 1.

TIMING DIAGRAMS




Figure 2.

TYPICAL CHARACTERISTICS

**UCC27200A IDD OPERATING CURRENT
VS
FREQUENCY**




Figure 3.

**UCC27201A IDD OPERATING CURRENT
VS
FREQUENCY**




Figure 4.

**BOOT VOLTAGE OPERATING CURRENT
VS
FREQUENCY**




Figure 5.

**HB TO VSS OPERATING CURRENT
VS
FREQUENCY**




Figure 6.

TYPICAL CHARACTERISTICS (continued)

**UCC27200A INPUT THRESHOLD
vs
SUPPLY VOLTAGE**




Figure 7.

**UCC27201A INPUT THRESHOLD
vs
SUPPLY VOLTAGE**




Figure 8.

**UCC27200A INPUT THRESHOLD
vs
TEMPERATURE**




Figure 9.

**UCC27201A INPUT THRESHOLD
vs
TEMPERATURE**




Figure 10.

TYPICAL CHARACTERISTICS (continued)

**LO AND HO HIGH LEVEL OUTPUT VOLTAGE
vs
TEMPERATURE**




Figure 11.

**LO AND HO LOW LEVEL OUTPUT VOLTAGE
vs
TEMPERATURE**




Figure 12.

**UNDervoltage LOCKOUT THRESHOLD
vs
TEMPERATURE**




Figure 13.

**UNDervoltage LOCKOUT THRESHOLD HYSTERESIS
vs
TEMPERATURE**




Figure 14.

TYPICAL CHARACTERISTICS (continued)

**UCC27200A PROPAGATION DELAYS
vs
TEMPERATURE**




Figure 15.

**UCC27201A PROPAGATION DELAYS
vs
TEMPERATURE**




Figure 16.

**UCC27200A PROPAGATION DELAY
vs
SUPPLY VOLTAGE**




Figure 17.

**UCC27201A PROPAGATION DELAY
vs
SUPPLY VOLTAGE**




Figure 18.


TYPICAL CHARACTERISTICS (continued)

Figure 19.




Figure 20.




Figure 21.




Figure 22.

APPLICATION INFORMATION

Functional Description

The UCC27200A and UCC27201A are high-side/low-side drivers. The high-side and low-side each have independent inputs which allow maximum flexibility of input control signals in the application. The boot diode for the high-side driver bias supply is internal to the UCC27200A and UCC27201A. The UCC27200A is the CMOS compatible input version and the UCC27201A is the TTL or logic compatible version. The high-side driver is referenced to the switch node (HS) which is typically the source pin of the high side MOSFET and drain pin of the low-side MOSFET. The low-side driver is referenced to VSS which is typically ground. The functions contained are the input stages, UVLO protection, level shift, boot diode, and output driver stages.

NOTE

The term “UCC2720x” applies to both the UCC27200A and UCC27201A.

Input Stages

The input stages provide the interface to the PWM output signals. The input impedance of the UCC27200A is 200 k Ω nominal and input capacitance is approximately 2 pF. The 200 k Ω is a pull-down resistance to Vss (ground). The CMOS compatible input of the UCC27200A provides a rising threshold of 48% of VDD and falling threshold of 45% of VDD. The inputs of the UCC27200A are intended to be driven from 0 to VDD levels.

The input stages of the UCC27201A incorporate an open drain configuration to provide the lower input thresholds. The input impedance is 200 k Ω nominal and input capacitance is approximately 4 pF. The 200 k Ω is a pull-down resistance to VSS (ground). The logic level compatible input provides a rising threshold of 1.7 V and a falling threshold of 1.6 V.

UVLO (Under Voltage Lockout)

The bias supplies for the high-side and low-side drivers have UVLO protection. VDD as well as VHB to VHS differential voltages are monitored. The VDD UVLO disables both drivers when VDD is below the specified threshold. The rising VDD threshold is 7.1 V with 0.5-V hysteresis. The VHB UVLO disables only the high-side driver when the VHB to VHS differential voltage is below the specified threshold. The VHB UVLO rising threshold is 6.7 V with 0.4-V hysteresis.

Level Shift

The level shift circuit is the interface from the high-side input to the high-side driver stage which is referenced to the switch node (HS). The level shift allows control of the HO output referenced to the HS pin and provides excellent delay matching with the low-side driver.

Boot Diode

The boot diode necessary to generate the high-side bias is included in the UCC2720x family of drivers. The diode anode is connected to VDD and cathode connected to VHB. With the VHB capacitor connected to HB and the HS pins, the VHB capacitor charge is refreshed every switching cycle when HS transitions to ground. The boot diode provides fast recovery times, low diode resistance, and voltage rating margin to allow for efficient and reliable operation.

Output Stages

The output stages are the interface to the power MOSFETs in the power train. High slew rate, low resistance and high peak current capability of both output drivers allow for efficient switching of the power MOSFETs. The low-side output stage is referenced from VDD to VSS and the high-side is referenced from VHB to VHS.

Design Tips

Switching the MOSFETs

Achieving optimum drive performance at high frequency efficiently requires special attention to layout and minimizing parasitic inductances. Care must be taken at the driver die and package level as well as the PCB layout to reduce parasitic inductances as much as possible. Figure 23 shows the main parasitic inductance elements and current flow paths during the turn ON and OFF of the MOSFET by charging and discharging its CGS capacitance.




Figure 23. MOSFET Drive Paths and Circuit Parasitics

The I_{SOURCE} current charges the C_{GS} gate capacitor and the I_{SINK} current discharges it. The rise and fall time of the voltage across the gate to source defines how quickly the MOSFET can be switched. Based on actual measurements, the analytical curves in Figure 24 and Figure 25 indicate the output voltage and current of the drivers during the discharge of the load capacitor. Figure 24 shows voltage and current as a function of time. Figure 25 indicates the relationship of voltage and current during fast switching. These figures demonstrate the actual switching process and limitations due to parasitic inductances.




Figure 24. Turn-Off Voltage and Current vs Time




Figure 25. Turn-Off Voltage and Current Switching Diagram

Turning off the MOSFET needs to be achieved as fast as possible to minimize switching losses. For this reason the UCC2720x drivers are designed for high peak currents and low output resistance. The sink capability is specified as 0.18 V at 100-mA dc current implying 1.8-Ω $R_{DS(on)}$. With 12-V drive voltage, no parasitic inductance and a linear resistance, one would expect initial sink current amplitude of 6.7 A for both high-side and low-side drivers. Assuming a pure R-C discharge circuit of the gate capacitor, one would expect the voltage and current waveforms to be exponential. Due to the parasitic inductances and non-linear resistance of the driver MOSFET'S, the actual waveforms have some ringing and the peak-sink current of the drivers is approximately 3.3 A as shown in Figure 20. The overall parasitic inductance of the drive circuit is estimated at 4 nH. The internal parasitic inductance of the SOIC-8 package is estimated to be 2 nH including bond wires and leads. The SON-8 package reduces the internal parasitic inductances by more than 50%.

Actual measured waveforms are shown in Figure 26 and Figure 27. As shown, the typical rise time of 8 ns and fall time of 7 ns is conservatively rated.

Saved: 25 AUG 2006 11:33:49

Saved: 25 AUG 2006 11:32:25




Figure 26. V_{LO} and V_{HO} Rise Time, 1-nF Load, 5 ns/Div




Figure 27. V_{LO} and V_{HO} Fall Time, 1-nF Load, 5-ns/Div

Dynamic Switching of the MOSFETs

The true behavior of MOSFETs presents a dynamic capacitive load primarily at the gate to source threshold voltage. Using the turn off case as the example, when the gate to source threshold voltage is reached the drain voltage starts rising, the drain to gate parasitic capacitance couples charge into the gate resulting in the turn off plateau. The relatively low threshold voltages of many MOSFETs and the increased charge that has to be removed (Miller charge) makes good driver performance necessary for efficient switching. An open loop half bridge power converter was utilized to evaluate performance in actual applications. The schematic of the half-bridge converter is shown in Figure 30. The turn off waveforms of the UCC27200A driving two MOSFETs in parallel is shown in Figure 28 and Figure 29.

Saved: 28 JUL 2006 18:48:20




Figure 28. V_{LO} Fall Time in Half-Bridge Converter

Saved: 28 JUL 2006 18:52:42




Figure 29. V_{HO} Fall Time in Half-Bridge Converter




Figure 30. Open Loop Half-Bridge Converter

Delay Matching and Narrow Pulse Widths

The total delays encountered in the PWM, driver and power stage need to be considered for a number of reasons, primarily delay in current limit response. Also to be considered are differences in delays between the drivers which can lead to various concerns depending on the topology. The sync-buck topology switching requires careful selection of dead-time between the high- and low-side switches to avoid 1) cross conduction and 2) excessive body diode conduction. Bridge topologies can be affected by a resulting volt-sec imbalance on the transformer if there is imbalance in the high and low side pulse widths in a steady state condition.

Narrow pulse width performance is an important consideration when transient and short circuit conditions are encountered. Although there may be relatively long steady state PWM output-driver-MOSFET signals, very narrow pulses may be encountered in 1) soft start, 2) large load transients, and 3) short circuit conditions.

The UCC2720x driver family offers excellent performance regarding high and low-side driver delay matching and narrow pulse width performance. The delay matching waveforms are shown in Figure 31 and Figure 32. The UCC2720x driver narrow pulse performance is shown in Figure 33 and Figure 34.




Figure 31. V_{LO} and V_{HO} Rising Edge Delay Matching




Figure 32. V_{LO} and V_{HO} Falling Edge Delay Matching



Figure 33. 20-ns Input Pulse Delay Matching




Figure 34. 10-ns Input Pulse Delay Matching

Boot Diode Performance

The UCC2720x family of drivers incorporates the bootstrap diode necessary to generate the high side bias internally. The characteristics of this diode are important to achieve efficient, reliable operation. The dc characteristics to consider are V_F and dynamic resistance. A low V_F and high dynamic resistance results in a high forward voltage during charging of the bootstrap capacitor. The UCC2720x has a boot diode rated at 0.65-V V_F and dynamic resistance of 0.6 Ω for reliable charge transfer to the bootstrap capacitor. The dynamic characteristics to consider are diode recovery time and stored charge. Diode recovery times that are specified with no conditions can be misleading. Diode recovery times at no forward current (I_F) can be noticeably less than with forward current applied. The UCC2720x boot diode recovery is specified at 20ns at $I_F = 20$ mA, $I_{REV} = 0.5$ A. At 0 mA I_F the reverse recovery time is 15 ns.

Another less obvious consideration is how the stored charge of the diode is affected by applied voltage. On every switching transition when the HS node transitions from low to high, charge is removed from the boot capacitor to charge the capacitance of the reverse biased diode. This is a portion of the driver power losses and reduces the voltage on the HB capacitor. At higher applied voltages, the stored charge of the UCC2720x PN diode is often less than a comparable Schottky diode.

Layout Recommendations

To improve the switching characteristics and efficiency of a design, the following layout rules should be followed.

- Locate the driver as close as possible to the MOSFETs.
- Locate the V_{DD} and V_{HB} (bootstrap) capacitors as close as possible to the driver.
- Pay close attention to the GND trace. Use the thermal pad of the DDA and DRM package as GND by connecting it to the VSS pin (GND). *Note: The GND trace from the driver goes directly to the source of the MOSFET but should not be in the high current path of the MOSFET(S) drain or source current.*
- Use similar rules for the HS node as for GND for the high side driver.
- Use wide traces for LO and HO closely following the associated GND or HS traces. 60 mil to 100 mil width is preferable where possible.
- Use as least two or more vias if the driver outputs or SW node needs to be routed from one layer to another. For GND the number of vias needs to be a consideration of the thermal pad requirements as well as parasitic inductance.
- Avoid L_I and H_I (driver input) going close to the HS node or any other high dV/dT traces that can induce significant noise into the relatively high impedance leads.
- Keep in mind that a poor layout can cause a significant drop in efficiency versus a good PCB layout and can even lead to decreased reliability of the whole system.




Figure 35. Example Component Placement

Additional References

These references and links to additional information may be found at www.ti.com.

1. Additional layout guidelines for PCB land patterns may be found in Application Brief SLUA271
2. Additional thermal performance guidelines may be found in Application Reports SLMA002A and SLMA004

REVISION HISTORY

| Changes from Original (February 2011) to Revision A | Page |
|--|------|
| • Added SON-10 (DPR) Package to the List of FEATURES | 1 |
| • Added SON-10 (DPR) Package to the DESCRIPTION | 2 |
| • Added the SON-10 package to the ORDERING INFORMATION table | 2 |
| • Added ordering information for the SON-10 (DPR) | 2 |
| • Added note, "DPR(SON-10) package comes either in a small reel of 250 pieces as part number UCC27200ADPRT, or large reels pieces as part number UCC27200ADPRR." | 2 |
| • Added the SON-10 package to the THERMAL INFORMATION table | 4 |
| • Changed the "Minimum input pulse width" value From: 50 ns Max To: 50 ns Typ | 6 |
| • Added the SON-10 package Pinout | 7 |
| • Changed the PIN FUNCTIONS table | 8 |
| • Added Additional PIN FUNCTIONS information. | 8 |

PACKAGING INFORMATION

| Orderable Device | Status (1) | Package Type | Package Drawing | Pins | Package Qty | Eco Plan (2) | Lead/Ball Finish (6) | MSL Peak Temp (3) | Op Temp (°C) | Device Marking (4/5) | Samples |
|------------------|---------------|--------------|--------------------|------|----------------|----------------------------|----------------------------|----------------------|--------------|-------------------------|-------------------------|
| UCC27200AD | ACTIVE | SOIC | D | 8 | 75 | Green (RoHS & no Sb/Br) | CU NIPDAU | Level-1-260C-UNLIM | -40 to 140 | 27200A | Samples |
| UCC27200ADDA | ACTIVE | SO PowerPAD | DDA | 8 | 75 | Green (RoHS & no Sb/Br) | CU NIPDAU | Level-1-260C-UNLIM | -40 to 140 | 27200A | Samples |
| UCC27200ADDAR | ACTIVE | SO PowerPAD | DDA | 8 | 2500 | Green (RoHS & no Sb/Br) | CU NIPDAU | Level-1-260C-UNLIM | -40 to 140 | 27200A | Samples |
| UCC27200ADR | ACTIVE | SOIC | D | 8 | 2500 | Green (RoHS & no Sb/Br) | CU NIPDAU | Level-1-260C-UNLIM | -40 to 140 | 27200A | Samples |
| UCC27200ADRCR | ACTIVE | VSON | DRC | 9 | 3000 | Green (RoHS & no Sb/Br) | CU NIPDAU | Level-2-260C-1 YEAR | -40 to 140 | 200A | Samples |
| UCC27200ADRCT | ACTIVE | VSON | DRC | 9 | 250 | Green (RoHS & no Sb/Br) | CU NIPDAU | Level-2-260C-1 YEAR | -40 to 140 | 200A | Samples |
| UCC27200ADRM | ACTIVE | VSON | DRM | 8 | 3000 | Green (RoHS & no Sb/Br) | CU NIPDAU | Level-1-260C-UNLIM | -40 to 140 | 27200A | Samples |
| UCC27200ADRMT | ACTIVE | VSON | DRM | 8 | 250 | Green (RoHS & no Sb/Br) | CU NIPDAU | Level-1-260C-UNLIM | -40 to 140 | 27200A | Samples |
| UCC27201AD | ACTIVE | SOIC | D | 8 | 75 | Green (RoHS & no Sb/Br) | CU NIPDAU | Level-1-260C-UNLIM | -40 to 140 | 27201A | Samples |
| UCC27201ADDA | ACTIVE | SO PowerPAD | DDA | 8 | 75 | Green (RoHS & no Sb/Br) | CU NIPDAU CU NIPDAUAG | Level-1-260C-UNLIM | -40 to 140 | 27201A | Samples |
| UCC27201ADDAR | ACTIVE | SO PowerPAD | DDA | 8 | 2500 | Green (RoHS & no Sb/Br) | CU NIPDAU CU NIPDAUAG | Level-1-260C-UNLIM | -40 to 140 | 27201A | Samples |
| UCC27201ADPRR | ACTIVE | WSO | DPR | 10 | 3000 | Green (RoHS & no Sb/Br) | CU NIPDAU | Level-2-260C-1 YEAR | -40 to 140 | UCC 27201A | Samples |
| UCC27201ADPRT | ACTIVE | WSO | DPR | 10 | 250 | Green (RoHS & no Sb/Br) | CU NIPDAU | Level-2-260C-1 YEAR | -40 to 140 | UCC 27201A | Samples |
| UCC27201ADR | ACTIVE | SOIC | D | 8 | 2500 | Green (RoHS & no Sb/Br) | CU NIPDAU | Level-1-260C-UNLIM | -40 to 140 | 27201A | Samples |
| UCC27201ADRCR | ACTIVE | VSON | DRC | 9 | 3000 | Green (RoHS & no Sb/Br) | CU NIPDAU | Level-2-260C-1 YEAR | -40 to 140 | 201A | Samples |
| UCC27201ADRCT | ACTIVE | VSON | DRC | 9 | 250 | Green (RoHS & no Sb/Br) | CU NIPDAU | Level-2-260C-1 YEAR | -40 to 140 | 201A | Samples |
| UCC27201ADRM | ACTIVE | VSON | DRM | 8 | 3000 | Green (RoHS & no Sb/Br) | CU NIPDAU | Level-1-260C-UNLIM | -40 to 140 | 27201A | Samples |

| Orderable Device | Status (1) | Package Type | Package Drawing | Pins | Package Qty | Eco Plan (2) | Lead/Ball Finish (6) | MSL Peak Temp (3) | Op Temp (°C) | Device Marking (4/5) | Samples |
|------------------|---------------|--------------|--------------------|------|----------------|----------------------------|-------------------------|----------------------|--------------|-------------------------|-------------------------|
| UCC27201ADRMT | ACTIVE | VSON | DRM | 8 | 250 | Green (RoHS & no Sb/Br) | CU NIPDAU | Level-1-260C-UNLIM | -40 to 140 | 27201A | Samples |

(1) The marketing status values are defined as follows:

ACTIVE: Product device recommended for new designs.

LIFEBUY: TI has announced that the device will be discontinued, and a lifetime-buy period is in effect.

NRND: Not recommended for new designs. Device is in production to support existing customers, but TI does not recommend using this part in a new design.

PREVIEW: Device has been announced but is not in production. Samples may or may not be available.

OBSOLETE: TI has discontinued the production of the device.

(2) Eco Plan - The planned eco-friendly classification: Pb-Free (RoHS), Pb-Free (RoHS Exempt), or Green (RoHS & no Sb/Br) - please check <http://www.ti.com/productcontent> for the latest availability information and additional product content details.

TBD: The Pb-Free/Green conversion plan has not been defined.

Pb-Free (RoHS): TI's terms "Lead-Free" or "Pb-Free" mean semiconductor products that are compatible with the current RoHS requirements for all 6 substances, including the requirement that lead not exceed 0.1% by weight in homogeneous materials. Where designed to be soldered at high temperatures, TI Pb-Free products are suitable for use in specified lead-free processes.

Pb-Free (RoHS Exempt): This component has a RoHS exemption for either 1) lead-based flip-chip solder bumps used between the die and package, or 2) lead-based die adhesive used between the die and leadframe. The component is otherwise considered Pb-Free (RoHS compatible) as defined above.

Green (RoHS & no Sb/Br): TI defines "Green" to mean Pb-Free (RoHS compatible), and free of Bromine (Br) and Antimony (Sb) based flame retardants (Br or Sb do not exceed 0.1% by weight in homogeneous material)

(3) MSL, Peak Temp. - The Moisture Sensitivity Level rating according to the JEDEC industry standard classifications, and peak solder temperature.

(4) There may be additional marking, which relates to the logo, the lot trace code information, or the environmental category on the device.

(5) Multiple Device Markings will be inside parentheses. Only one Device Marking contained in parentheses and separated by a "~" will appear on a device. If a line is indented then it is a continuation of the previous line and the two combined represent the entire Device Marking for that device.

(6) Lead/Ball Finish - Orderable Devices may have multiple material finish options. Finish options are separated by a vertical ruled line. Lead/Ball Finish values may wrap to two lines if the finish value exceeds the maximum column width.

Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

TAPE AND REEL INFORMATION


*All dimensions are nominal

| Device | Package Type | Package Drawing | Pins | SPQ | Reel Diameter (mm) | Reel Width W1 (mm) | A0 (mm) | B0 (mm) | K0 (mm) | P1 (mm) | W (mm) | Pin1 Quadrant |
|---------------|--------------|-----------------|------|------|--------------------|--------------------|---------|---------|---------|---------|--------|---------------|
| UCC27200ADDAR | SO Power PAD | DDA | 8 | 2500 | 330.0 | 12.4 | 6.4 | 5.2 | 2.1 | 8.0 | 12.0 | Q1 |
| UCC27200ADRCR | VSON | DRC | 9 | 3000 | 330.0 | 12.4 | 3.3 | 3.3 | 1.1 | 8.0 | 12.0 | Q2 |
| UCC27200ADRCT | VSON | DRC | 9 | 250 | 180.0 | 12.4 | 3.3 | 3.3 | 1.1 | 8.0 | 12.0 | Q2 |
| UCC27201ADDAR | SO Power PAD | DDA | 8 | 2500 | 330.0 | 12.4 | 6.4 | 5.2 | 2.1 | 8.0 | 12.0 | Q1 |
| UCC27201ADDAR | SO Power PAD | DDA | 8 | 2500 | 330.0 | 12.8 | 6.4 | 5.2 | 2.1 | 8.0 | 12.0 | Q1 |
| UCC27201ADPRR | WSO | DPR | 10 | 3000 | 330.0 | 12.4 | 4.25 | 4.25 | 1.15 | 8.0 | 12.0 | Q2 |
| UCC27201ADPRT | WSO | DPR | 10 | 250 | 180.0 | 12.4 | 4.25 | 4.25 | 1.15 | 8.0 | 12.0 | Q2 |
| UCC27201ADRCR | VSON | DRC | 9 | 3000 | 330.0 | 12.4 | 3.3 | 3.3 | 1.1 | 8.0 | 12.0 | Q2 |
| UCC27201ADRCT | VSON | DRC | 9 | 250 | 180.0 | 12.4 | 3.3 | 3.3 | 1.1 | 8.0 | 12.0 | Q2 |
| UCC27201ADRM | VSON | DRM | 8 | 3000 | 330.0 | 12.4 | 4.25 | 4.25 | 1.15 | 8.0 | 12.0 | Q2 |
| UCC27201ADRM | VSON | DRM | 8 | 250 | 180.0 | 12.4 | 4.25 | 4.25 | 1.15 | 8.0 | 12.0 | Q2 |

TAPE AND REEL BOX DIMENSIONS



*All dimensions are nominal

| Device | Package Type | Package Drawing | Pins | SPQ | Length (mm) | Width (mm) | Height (mm) |
|---------------|--------------|-----------------|------|------|-------------|------------|-------------|
| UCC27200ADDAR | SO PowerPAD | DDA | 8 | 2500 | 367.0 | 367.0 | 35.0 |
| UCC27200ADRCR | VSON | DRC | 9 | 3000 | 367.0 | 367.0 | 35.0 |
| UCC27200ADRCT | VSON | DRC | 9 | 250 | 210.0 | 185.0 | 35.0 |
| UCC27201ADDAR | SO PowerPAD | DDA | 8 | 2500 | 367.0 | 367.0 | 35.0 |
| UCC27201ADDAR | SO PowerPAD | DDA | 8 | 2500 | 364.0 | 364.0 | 27.0 |
| UCC27201ADPRR | WSON | DPR | 10 | 3000 | 367.0 | 367.0 | 35.0 |
| UCC27201ADPRT | WSON | DPR | 10 | 250 | 210.0 | 185.0 | 35.0 |
| UCC27201ADRCR | VSON | DRC | 9 | 3000 | 367.0 | 367.0 | 35.0 |
| UCC27201ADRCT | VSON | DRC | 9 | 250 | 210.0 | 185.0 | 35.0 |
| UCC27201ADRM | VSON | DRM | 8 | 3000 | 367.0 | 367.0 | 35.0 |
| UCC27201ADRM | VSON | DRM | 8 | 250 | 210.0 | 185.0 | 35.0 |

DDA (R-PDSO-G8)

PowerPAD™ PLASTIC SMALL-OUTLINE



- NOTES:
- All linear dimensions are in millimeters. Dimensioning and tolerancing per ASME Y14.5-1994.
 - This drawing is subject to change without notice.
 - Body dimensions do not include mold flash or protrusion not to exceed 0,15.
 - This package is designed to be soldered to a thermal pad on the board. Refer to Technical Brief, PowerPad Thermally Enhanced Package, Texas Instruments Literature No. SLMA002 for information regarding recommended board layout. This document is available at www.ti.com <<http://www.ti.com>>.
 - See the additional figure in the Product Data Sheet for details regarding the exposed thermal pad features and dimensions.
 - This package complies to JEDEC MS-012 variation BA

PowerPAD is a trademark of Texas Instruments.

DDA (R-PDSO-G8)


PowerPAD™ PLASTIC SMALL OUTLINE

THERMAL INFORMATION

This PowerPAD™ package incorporates an exposed thermal pad that is designed to be attached to a printed circuit board (PCB). The thermal pad must be soldered directly to the PCB. After soldering, the PCB can be used as a heatsink. In addition, through the use of thermal vias, the thermal pad can be attached directly to the appropriate copper plane shown in the electrical schematic for the device, or alternatively, can be attached to a special heatsink structure designed into the PCB. This design optimizes the heat transfer from the integrated circuit (IC).

For additional information on the PowerPAD package and how to take advantage of its heat dissipating abilities, refer to Technical Brief, PowerPAD Thermally Enhanced Package, Texas Instruments Literature No. SLMA002 and Application Brief, PowerPAD Made Easy, Texas Instruments Literature No. SLMA004. Both documents are available at www.ti.com.

The exposed thermal pad dimensions for this package are shown in the following illustration.



Exposed Thermal Pad Dimensions

4206322-8/L 05/12

NOTE: A. All linear dimensions are in millimeters

PowerPAD is a trademark of Texas Instruments

DDA (R-PDSO-G8)


PowerPAD™ PLASTIC SMALL OUTLINE

THERMAL INFORMATION

This PowerPAD™ package incorporates an exposed thermal pad that is designed to be attached to a printed circuit board (PCB). The thermal pad must be soldered directly to the PCB. After soldering, the PCB can be used as a heatsink. In addition, through the use of thermal vias, the thermal pad can be attached directly to the appropriate copper plane shown in the electrical schematic for the device, or alternatively, can be attached to a special heatsink structure designed into the PCB. This design optimizes the heat transfer from the integrated circuit (IC).

For additional information on the PowerPAD package and how to take advantage of its heat dissipating abilities, refer to Technical Brief, PowerPAD Thermally Enhanced Package, Texas Instruments Literature No. SLMA002 and Application Brief, PowerPAD Made Easy, Texas Instruments Literature No. SLMA004. Both documents are available at www.ti.com.

The exposed thermal pad dimensions for this package are shown in the following illustration.



Exposed Thermal Pad Dimensions


4206322-5/L 05/12

NOTE: A. All linear dimensions are in millimeters

PowerPAD is a trademark of Texas Instruments

DDA (R-PDSO-G8)

PowerPAD™ PLASTIC SMALL OUTLINE




- NOTES:
- All linear dimensions are in millimeters.
 - This drawing is subject to change without notice.
 - Customers should place a note on the circuit board fabrication drawing not to alter the center solder mask defined pad.
 - This package is designed to be soldered to a thermal pad on the board. Refer to Technical Brief, PowerPad Thermally Enhanced Package, Texas Instruments Literature No. SLMA002, SLMA004, and also the Product Data Sheets for specific thermal information, via requirements, and recommended board layout. These documents are available at www.ti.com <<http://www.ti.com>>. Publication IPC-7351 is recommended for alternate designs.
 - Laser cutting apertures with trapezoidal walls and also rounding corners will offer better paste release. Customers should contact their board assembly site for stencil design recommendations. Example stencil design based on a 50% volumetric metal load solder paste. Refer to IPC-7525 for other stencil recommendations.
 - Customers should contact their board fabrication site for solder mask tolerances between and around signal pads.


PowerPAD is a trademark of Texas Instruments.

DRM (S-PVSON-N8)

PLASTIC SMALL OUTLINE NO-LEAD



4205854/C 02/11


- NOTES:
- A. All linear dimensions are in millimeters. Dimensioning and tolerancing per ASME Y14.5M-1994.
 - B. This drawing is subject to change without notice.
 - C. SON (Small Outline No-Lead) package configuration.
 -  D. The package thermal pad must be soldered to the board for thermal and mechanical performance. See the Product Data Sheet for details regarding the exposed thermal pad dimensions.

THERMAL INFORMATION

This package incorporates an exposed thermal pad that is designed to be attached directly to an external heatsink. The thermal pad must be soldered directly to the printed circuit board (PCB). After soldering, the PCB can be used as a heatsink. In addition, through the use of thermal vias, the thermal pad can be attached directly to the appropriate copper plane shown in the electrical schematic for the device, or alternatively, can be attached to a special heatsink structure designed into the PCB. This design optimizes the heat transfer from the integrated circuit (IC).

For information on the Quad Flatpack No-Lead (QFN) package and its advantages, refer to Application Report, Quad Flatpack No-Lead Logic Packages, Texas Instruments Literature No. SCBA017. This document is available at www.ti.com.


The exposed thermal pad dimensions for this package are shown in the following illustration.



NOTE: All linear dimensions are in millimeters

Exposed Thermal Pad Dimensions


DRM (S-PDSO-N8)



- NOTES:
- A. All linear dimensions are in millimeters.
 - B. This drawing is subject to change without notice.
 - C. Publication IPC-7351 is recommended for alternate designs.
 - D. This package is designed to be soldered to a thermal pad on the board. Refer to Application Note, QFN Packages, Texas Instruments Literature No. SCBA017, SLUA271, and also the Product Data Sheets for specific thermal information, via requirements, and recommended board layout. These documents are available at www.ti.com <<http://www.ti.com>>.
 - E. Laser cutting apertures with trapezoidal walls and also rounding corners will offer better paste release. Customers should contact their board assembly site for stencil design recommendations. Refer to IPC 7525 for stencil design considerations.
 - F. Customers should contact their board fabrication site for solder mask tolerances.

DRC (S-PVSON-N9)

PLASTIC SMALL OUTLINE NO-LEAD



4204102-2/L 09/11

- NOTES:
- All linear dimensions are in millimeters. Dimensioning and tolerancing per ASME Y14.5M-1994.
 - This drawing is subject to change without notice.
 - Small Outline No-Lead (SON) package configuration.
 - The package thermal pad must be soldered to the board for thermal and mechanical performance, if present.
 - See the additional figure in the Product Data Sheet for details regarding the exposed thermal pad features and dimensions, if present.

DRC (S-PVSON-N9)


PLASTIC SMALL OUTLINE NO-LEAD

THERMAL INFORMATION

This package incorporates an exposed thermal pad that is designed to be attached directly to an external heatsink. The thermal pad must be soldered directly to the printed circuit board (PCB). After soldering, the PCB can be used as a heatsink. In addition, through the use of thermal vias, the thermal pad can be attached directly to the appropriate copper plane shown in the electrical schematic for the device, or alternatively, can be attached to a special heatsink structure designed into the PCB. This design optimizes the heat transfer from the integrated circuit (IC).

For information on the Quad Flatpack No-Lead (QFN) package and its advantages, refer to Application Report, QFN/SON PCB Attachment, Texas Instruments Literature No. SLUA271. This document is available at www.ti.com.

The exposed thermal pad dimensions for this package are shown in the following illustration.




Exposed Thermal Pad Dimensions

4206565-2/U 04/14

NOTE: A. All linear dimensions are in millimeters

DRC (S-PVSON-N9)


PLASTIC SMALL OUTLINE NO-LEAD



- NOTES:
- All linear dimensions are in millimeters.
 - This drawing is subject to change without notice.
 - This package is designed to be soldered to a thermal pad on the board. Refer to Application Note, Quad Flat-Pack Packages, Texas Instruments Literature No. SLUA271, and also the Product Data Sheets for specific thermal information, via requirements, and recommended board layout. These documents are available at www.ti.com <<http://www.ti.com>>.
 - Laser cutting apertures with trapezoidal walls and also rounding corners will offer better paste release. Customers should contact their board assembly site for stencil design recommendations. Refer to IPC 7525 for stencil design considerations.
 - Customers should contact their board fabrication site for minimum solder mask web tolerances between signal pads and via tenting recommendations for any larger diameter vias placed in the thermal pad.

DPR (S-PWSON-N10)

PLASTIC SMALL OUTLINE NO-LEAD



4211532/B 04/12

- NOTES:
- All linear dimensions are in millimeters. Dimensioning and tolerancing per ASME Y14.5M-1994.
 - This drawing is subject to change without notice.
 - SON (Small Outline No-Lead) package configuration.
 - The package thermal pad must be soldered to the board for thermal and mechanical performance.
 - See the additional figure in the Product Data Sheet for details regarding the exposed thermal pad features and dimensions.

THERMAL PAD MECHANICAL DATA

DPR (S-PWSON-N10)


PLASTIC SMALL OUTLINE NO-LEAD

THERMAL INFORMATION

This package incorporates an exposed thermal pad that is designed to be attached directly to an external heatsink. The thermal pad must be soldered directly to the printed circuit board (PCB). After soldering, the PCB can be used as a heatsink. In addition, through the use of thermal vias, the thermal pad can be attached directly to the appropriate copper plane shown in the electrical schematic for the device, or alternatively, can be attached to a special heatsink structure designed into the PCB. This design optimizes the heat transfer from the integrated circuit (IC).

For information on the Quad Flatpack No-Lead (QFN) package and its advantages, refer to Application Report, QFN/SON PCB Attachment, Texas Instruments Literature No. SLUA271. This document is available at www.ti.com.

The exposed thermal pad dimensions for this package are shown in the following illustration.




4211551/C 12/13

NOTES: All linear dimensions are in millimeters

DPR (S-PWSON-N10)

PLASTIC SMALL OUTLINE NO-LEAD



- NOTES:
- A. All linear dimensions are in millimeters.
 - B. This drawing is subject to change without notice.
 - C. Publication IPC-7351 is recommended for alternate designs.
 - D. This package is designed to be soldered to a thermal pad on the board. Refer to Application Note, Quad Flat-Pack Packages, Texas Instruments Literature No. SLUA271, and also the Product Data Sheets for specific thermal information, via requirements, and recommended board layout. These documents are available at www.ti.com <<http://www.ti.com>>.
 - E. Laser cutting apertures with trapezoidal walls and also rounding corners will offer better paste release. Customers should contact their board assembly site for stencil design recommendations. Refer to IPC 7525 for stencil design considerations.
 - F. Customers should contact their board fabrication site for recommended solder mask tolerances and via tenting recommendations for vias placed in the thermal pad.

D (R-PDSO-G8)

PLASTIC SMALL OUTLINE



NOTES:

- A. All linear dimensions are in inches (millimeters).
- B. This drawing is subject to change without notice.
- $\triangle C$ Body length does not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not exceed 0.006 (0,15) each side.
- $\triangle D$ Body width does not include interlead flash. Interlead flash shall not exceed 0.017 (0,43) each side.
- E. Reference JEDEC MS-012 variation AA.

D (R-PDSO-G8)

PLASTIC SMALL OUTLINE



4211283-2/E 08/12

- NOTES:
- A. All linear dimensions are in millimeters.
 - B. This drawing is subject to change without notice.
 - C. Publication IPC-7351 is recommended for alternate designs.
 - D. Laser cutting apertures with trapezoidal walls and also rounding corners will offer better paste release. Customers should contact their board assembly site for stencil design recommendations. Refer to IPC-7525 for other stencil recommendations.
 - E. Customers should contact their board fabrication site for solder mask tolerances between and around signal pads.

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, enhancements, improvements and other changes to its semiconductor products and services per JESD46, latest issue, and to discontinue any product or service per JESD48, latest issue. Buyers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All semiconductor products (also referred to herein as "components") are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its components to the specifications applicable at the time of sale, in accordance with the warranty in TI's terms and conditions of sale of semiconductor products. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by applicable law, testing of all parameters of each component is not necessarily performed.

TI assumes no liability for applications assistance or the design of Buyers' products. Buyers are responsible for their products and applications using TI components. To minimize the risks associated with Buyers' products and applications, Buyers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI components or services are used. Information published by TI regarding third-party products or services does not constitute a license to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of significant portions of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI components or services with statements different from or beyond the parameters stated by TI for that component or service voids all express and any implied warranties for the associated TI component or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Buyer acknowledges and agrees that it is solely responsible for compliance with all legal, regulatory and safety-related requirements concerning its products, and any use of TI components in its applications, notwithstanding any applications-related information or support that may be provided by TI. Buyer represents and agrees that it has all the necessary expertise to create and implement safeguards which anticipate dangerous consequences of failures, monitor failures and their consequences, lessen the likelihood of failures that might cause harm and take appropriate remedial actions. Buyer will fully indemnify TI and its representatives against any damages arising out of the use of any TI components in safety-critical applications.

In some cases, TI components may be promoted specifically to facilitate safety-related applications. With such components, TI's goal is to help enable customers to design and create their own end-product solutions that meet applicable functional safety standards and requirements. Nonetheless, such components are subject to these terms.

No TI components are authorized for use in FDA Class III (or similar life-critical medical equipment) unless authorized officers of the parties have executed a special agreement specifically governing such use.

Only those TI components which TI has specifically designated as military grade or "enhanced plastic" are designed and intended for use in military/aerospace applications or environments. Buyer acknowledges and agrees that any military or aerospace use of TI components which have **not** been so designated is solely at the Buyer's risk, and that Buyer is solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI has specifically designated certain components as meeting ISO/TS16949 requirements, mainly for automotive use. In any case of use of non-designated products, TI will not be responsible for any failure to meet ISO/TS16949.

Products

| | |
|------------------------------|--|
| Audio | www.ti.com/audio |
| Amplifiers | amplifier.ti.com |
| Data Converters | dataconverter.ti.com |
| DLP® Products | www.dlp.com |
| DSP | dsp.ti.com |
| Clocks and Timers | www.ti.com/clocks |
| Interface | interface.ti.com |
| Logic | logic.ti.com |
| Power Mgmt | power.ti.com |
| Microcontrollers | microcontroller.ti.com |
| RFID | www.ti-rfid.com |
| OMAP Applications Processors | www.ti.com/omap |
| Wireless Connectivity | www.ti.com/wirelessconnectivity |

Applications

| | |
|-------------------------------|--|
| Automotive and Transportation | www.ti.com/automotive |
| Communications and Telecom | www.ti.com/communications |
| Computers and Peripherals | www.ti.com/computers |
| Consumer Electronics | www.ti.com/consumer-apps |
| Energy and Lighting | www.ti.com/energy |
| Industrial | www.ti.com/industrial |
| Medical | www.ti.com/medical |
| Security | www.ti.com/security |
| Space, Avionics and Defense | www.ti.com/space-avionics-defense |
| Video and Imaging | www.ti.com/video |

TI E2E Community

e2e.ti.com

AMEYA360

Components Supply Platform

Authorized Distribution Brand :



Website :

Welcome to visit www.ameya360.com

Contact Us :

➤ Address :

401 Building No.5, JiuGe Business Center, Lane 2301, Yishan Rd
Minhang District, Shanghai , China

➤ Sales :

Direct +86 (21) 6401-6692

Email amall@ameya360.com

QQ 800077892

Skype ameyasales1 ameyasales2

➤ Customer Service :

Email service@ameya360.com

➤ Partnership :

Tel +86 (21) 64016692-8333

Email mkt@ameya360.com