

# POWER TRANSFORMER CHASSIS MOUNT: QUICK-CONNECT WORLD SERIES $^{\text{TM}}$

# **VPS24-1000**

#### Electrical Specifications (@25C)

- 1. Maximum Power: 25VA
- 2. Primary Series: 230VAC@50/60Hz; Parallel: 115VAC@50/60Hz
- 3. Secondary Series1: 24V CT@ 1.0A; Parallel2: 12.0V @ 2.0A
- 4. Voltage Regulation: 25% TYP @ full load to no load
- 5. Temperature Rise: 30C TYP (45C MAX allowed)
- 6. Insulation Resistance:  $100M\Omega$
- 7. Recommended Fuse<sup>3</sup>:

Series: Littelfuse p/n 313 1.25HXP, 1.25A 250V, slow blow, ¼ x 1 ¼ or, Cooper Bussmann p/n BKMDL-1 ¼, 1.25A 250V, ¼ x 1 ¼ Parallel: Littelfuse p/n 313 2.5HXP, 2.5A 250V, slow blow, ¼ x 1 ¼ or, Cooper Bussmann p/n BKMDL-2 ½, 2.5A 250V, ¼ x 1 ¼

#### Construction:

Dual bobbin construction with an insulated shroud, both made of a high temperature material that exceeds UL flammability requirements.

#### Safety:

These units are designed with 4000VAC isolation between the primary and secondary, and also, between each winding and the core.

#### **Agency File:**

UL: File E53148, UL 5085-1 and 2 (formerly UL 506), General Purpose. File E65390, UL 5085-1 and 3 (formerly UL1585), Class 2/3

CSA: File LR 221330. C22.2 NO. 66, General Purpose.

TUV Certificate No.: R72103639, EN60950, Information Technology







A. Dimensions:						ι	Unit: In inches	
Н	W	D	Α	В	С	Т	MW	ML
2-5/16	2-13/16	1-15/16	2	1-1/8	5/16	3/16	2-3/8	-

B. Mounting Hole Size: 3/16"

C. WT Lbs.: 1.25

#### Connections4:

**Input:** Series – 6 and 1, Jumper 5 to 2

Parallel - 6 and 1, Jumper 6 to 2 and 5 to 1


Output: Series - 12 and 7, Jumper 11 to 8

Parallel - 12 and 7, Jumper 12 to 8 and 11 to 7


**RoHS Compliance:** As of manufacturing date February 2005, all standard products meet the requirements of 2002/95/EC, known as the RoHS initiative.


\* Upon printing, this document is considered "uncontrolled". Please contact Triad Magnetics' website for the most current version.


<sup>&</sup>lt;sup>4</sup> Primary and secondary windings are designed to be connected in series or parallel. Winding are not intended to be used independently.














**SCHEMATIC** 

Web: www.TriadMagnetics.com Phone 951-277-0757 Fax 951-277-2757

Release Date: September 13, 2012

<sup>&</sup>lt;sup>1</sup> Non-Inherently limited. Class 3.

<sup>&</sup>lt;sup>2</sup> Non-Inherently limited. Class 2 not wet, Class 3 wet.

<sup>&</sup>lt;sup>3</sup> Fuse must be used on **secondary** as conditions of acceptability for UL Class2/3 operation.

# AMEYA360 Components Supply Platform

# **Authorized Distribution Brand:**

























## Website:

Welcome to visit www.ameya360.com

#### Contact Us:

### Address:

401 Building No.5, JiuGe Business Center, Lane 2301, Yishan Rd Minhang District, Shanghai , China

#### > Sales:

Direct +86 (21) 6401-6692

Email amall@ameya360.com

QQ 800077892

Skype ameyasales1 ameyasales2

### Customer Service :

Email service@ameya360.com

# Partnership :

Tel +86 (21) 64016692-8333

Email mkt@ameya360.com