

2N4416, 2N4416A

N-Channel Silicon Junction Field-Effect Transistor

- Mixers
- VHF Amplifiers

Absolute maximum ratings at $T_A = 25^\circ\text{C}$

Reverse Gate Source & Reverse Gate Drain Voltage	2N4416	- 30 V	2N4416A	- 35 V
Gate Current		10 mA		10 mA
Continuous Device Dissipation		300 mW		300 mW
Power Derating		2 mW/°C		2 mW/°C

At 25°C free air temperature:

Static Electrical Characteristics

		2N4416		2N4416A		Process NJ26	
		Min	Max	Min	Max	Unit	Test Conditions
Gate Source Breakdown Voltage	$V_{(BR)GSS}$	- 30		- 35		V	$I_G = -1\mu\text{A}$, $V_{DS} = \emptyset\text{V}$
Gate Reverse Current	I_{GSS}		- 0.1		- 0.1	nA	$V_{GS} = -20\text{V}$, $V_{DS} = \emptyset\text{V}$
			- 0.1		- 0.1	μA	$V_{GS} = -20\text{V}$, $V_{DS} = \emptyset\text{V}$, $T_A = 150^\circ\text{C}$
Gate Source Cutoff Voltage	$V_{GS(OFF)}$		- 6	- 2.5	- 6	V	$V_{DS} = 15\text{V}$, $I_D = 1\text{nA}$
Drain Saturation Current (Pulsed)	I_{DSS}	5	15	5	15	mA	$V_{DS} = 15\text{V}$, $V_{GS} = \emptyset\text{V}$

Dynamic Electrical Characteristics

Common Source Forward Transconductance	g_{fs}	4500	7500	4500	7500	μS	$V_{DS} = 15\text{V}$, $V_{GS} = \emptyset\text{V}$	$f = 1\text{ kHz}$
		4000		4000		μS	$V_{DS} = 15\text{V}$, $V_{GS} = \emptyset\text{V}$	$f = 400\text{ MHz}$
Common Source Output Conductance	g_{os}		50		50	μS	$V_{DS} = 15\text{V}$, $V_{GS} = \emptyset\text{V}$	$f = 1\text{ kHz}$
			75		75	μS	$V_{DS} = 15\text{V}$, $V_{GS} = \emptyset\text{V}$	$f = 100\text{ MHz}$
			100		100	μS	$V_{DS} = 15\text{V}$, $V_{GS} = \emptyset\text{V}$	$f = 400\text{ MHz}$
Common Source Input Capacitance	C_{iss}		4		4	pF	$V_{DS} = 15\text{V}$, $V_{GS} = \emptyset\text{V}$	$f = 1\text{ MHz}$
Common Source Output Capacitance	C_{oss}		2		2	pF	$V_{DS} = 15\text{V}$, $V_{GS} = \emptyset\text{V}$	$f = 1\text{ MHz}$
Common Source Reverse Transfer Capacitance	C_{rss}		0.8		0.8	pF	$V_{DS} = 15\text{V}$, $V_{GS} = \emptyset\text{V}$	$f = 1\text{ MHz}$
Common Source Input Conductance	g_{is}		100		100	μS	$V_{DS} = 15\text{V}$, $V_{GS} = \emptyset\text{V}$	$f = 100\text{ MHz}$
			1000		1000	μS	$V_{DS} = 15\text{V}$, $V_{GS} = \emptyset\text{V}$	$f = 400\text{ MHz}$
Common Source Input Susceptance	b_{is}		2500		2500	μS	$V_{DS} = 15\text{V}$, $V_{GS} = \emptyset\text{V}$	$f = 100\text{ MHz}$
			10000		10000	μS	$V_{DS} = 15\text{V}$, $V_{GS} = \emptyset\text{V}$	$f = 400\text{ MHz}$
Common Source Output Susceptance	b_{os}		1000		1000	μS	$V_{DS} = 15\text{V}$, $V_{GS} = \emptyset\text{V}$	$f = 100\text{ MHz}$
			4000		4000	μS	$V_{DS} = 15\text{V}$, $V_{GS} = \emptyset\text{V}$	$f = 400\text{ MHz}$
Common Source Power Gain	G_{ps}	18		18		dB	$V_{DS} = 15\text{V}$, $I_D = 5\text{mA}$	$f = 100\text{ MHz}$
		10		10		dB	$V_{DS} = 15\text{V}$, $I_D = 5\text{mA}$	$f = 400\text{ MHz}$
Noise Figure	NF		2		2	dB	$V_{DS} = 15\text{V}$, $I_D = 5\text{mA}$	$f = 100\text{ MHz}$
			4		4	dB	$R_G = 1\text{k}\Omega$	$f = 400\text{ MHz}$

Note: rf parameters guaranteed, but not 100% tested.

TO-72 Package

See Section G for Outline Dimensions

Pin Configuration

1 Source, 2 Drain, 3 Gate, 4 Case

Surface Mount

SMP4416, SMP4416A



715 N. Glenville Dr., Richardson, TX 75081
(972) 238-1287 Fax (972) 238-5338

www.interfet.com

AMEYA360

Components Supply Platform

Authorized Distribution Brand :



Website :

Welcome to visit www.ameya360.com

Contact Us :

➤ Address :

401 Building No.5, JiuGe Business Center, Lane 2301, Yishan Rd
Minhang District, Shanghai , China

➤ Sales :

Direct +86 (21) 6401-6692
Email amall@ameya360.com
QQ 800077892
Skype ameyasales1 ameyasales2

➤ Customer Service :

Email service@ameya360.com

➤ Partnership :

Tel +86 (21) 64016692-8333
Email mkt@ameya360.com