



## Comprehensive DSP Tool Solutions

[Home » Emulators » 701967](#)

### Documentation

[Installation Guide](#)

[Drivers and Support](#)

### Application

Debug hardware

Debug software

Flash programming

**Warranty:** 1 year from date of purchase on Emulator, for Code Composer Studio™ refer to TI Website

## XDS510 USB Galvanic JTAG Emulator with Code Composer Studio™ Platinum version 3.3



**Part #:** 701967

**Rev Level:** A

XDS510 USB Galvanic JTAG Emulator with Code Composer Studio™ Platinum version 3.3

System Features	System Features	What's Included
<ul style="list-style-type: none"> <li>Supports Texas Instruments Digital Signal Processors and Microcontrollers with <b>JTAG</b> interface:               <ul style="list-style-type: none"> <li>F24xx • F28xx</li> <li>C54xx • C55xx</li> <li>C67xx • C672x</li> <li>C62xx • C641x</li> <li>C642x • C645x</li> <li>C64x+ • DM64x</li> <li>C674x • DM355</li> <li>DaVinci™ TMS570</li> <li>TMS470 Cortex™</li> <li>OMAP™</li> </ul> </li> </ul>	<ul style="list-style-type: none"> <li>Operates off PC/laptop USB port, <b>no</b> internal adapter required</li> <li>USB bus powered, <b>no</b> power supply required</li> <li>Supports USB 1.x and USB 2.0 (full speed)</li> <li>Advanced emulation controller provides high performance</li> <li>Compatible with +3.3V or +5V processors</li> <li>One LED provides operational status</li> <li>Voltage isolation provided by IL715, IL717, HCPL-260L (UL1577 rated for 2500Vrms for 1 minute and IEC 61010-1, Pollution Degree II, Material Group III, Max Working Voltage 300 Vrms Common Mode)</li> </ul>	<ul style="list-style-type: none"> <li>Code Composer Studio™ Platinum version 3.3</li> <li>XDS510 USB Galvanic JTAG Emulator</li> <li>USB cable</li> <li>CD-ROM with drivers</li> <li>Setup instructions</li> <li>Warranty registration card</li> <li>Technical reference manual</li> </ul>
Software Features		You May Need
<ul style="list-style-type: none"> <li>Code Composer Studio™ Platinum version 3.3 from Texas Instruments.</li> </ul>		<ul style="list-style-type: none"> <li>4 Channel JTAG Expander</li> <li>DSP Target Board (EVM, eZdsp, DSK)</li> </ul>

- |   |   |  |
|---|---|--|
| <ul style="list-style-type: none"><li>• Supports Code Composer Studio™ FlashBurn utility.</li><li>• Compatible with Spectrum Digital “SDFlash” Programming utility</li><li>• Compatible with ‘C’ Language “XMLGUI” interface</li><li>• Compatible with Windows 2000, XP, and Vista(32/64 bit)</li></ul> | <p>Transient Immunity 30Kv/us @ Vcm=300V)</p> <ul style="list-style-type: none"><li>• Voltage isolation on PWB with 6mm minimum clearances and creepage distances</li></ul> |  |
|---|---|--|

# AMEYA360

Components Supply Platform

Authorized Distribution Brand :



Website :

Welcome to visit [www.ameya360.com](http://www.ameya360.com)

Contact Us :

➤ Address :

401 Building No.5, JiuGe Business Center, Lane 2301, Yishan Rd  
Minhang District, Shanghai , China

➤ Sales :

Direct     +86 (21) 6401-6692  
  
Email        amall@ameya360.com  
  
QQ           800077892  
  
Skype        ameyasales1 ameyasales2

➤ Customer Service :

Email        service@ameya360.com

➤ Partnership :

Tel           +86 (21) 64016692-8333  
  
Email        mkt@ameya360.com