

Ohmite radio frequency plate chokes have a single-layer winding designed to avoid adverse harmonic effects and prevents breakdown from high r.f. potentials. Windings are insulated and protected by a moisture-proof coating.

- Z-7 type furnished with non-magnetic mounting bracket.
- Z-14, Z-28 type have wire leads welded to lug type terminals.
- Z-50, Z-144, Z-235, Z-460 type have axial wire leads.

It is generally advisable to select a choke with a resonant frequency (see chart) slightly higher than the desired operating frequency since any additional capacity to ground will tend to shift the resonant frequency closer to the operating frequency.



Z Series

R. F. Plate Chokes



ORDERING INFO

RoHS Compliant

Z - 1 4 4 E

Z Series Specifier
see chart

STOCK PART NUMBERS								
Part number	Inductance (μH) ±10% @ 1kHz	Rated DC current (A)	DCR (Ω)	Operating range (MHz)	SRF (MHz)	Diameter (in./mm)	Length (in./mm)	
Z-7	84.0	1.00	4.70	3 - 20	13	0.563 / 14.29	6	152.4
Z-14	44.0	0.68	2.60	7 - 35	23	0.438 / 11.11	2	50.6
Z-28	21.0	0.60	2.70	20 - 60	41	0.313 / 7.94	1.750	44.45
Z-50	7.0	1.00	0.98	35 - 110	79	0.281 / 7.14	1	25.4
Z-144	1.8	1.10	0.33	80 - 200	168	0.188 / 4.76	0.750	19.05
Z-235	0.84	1.70	0.14	160 - 350	300	0.188 / 4.76	0.750	19.05
Z-460	0.20	4.00	0.034	320 - 520	500	0.156 / 3.97	0.500	12.70

AMEYA360

Components Supply Platform

Authorized Distribution Brand :



Website :

Welcome to visit www.ameya360.com

Contact Us :

➤ Address :

401 Building No.5, JiuGe Business Center, Lane 2301, Yishan Rd
Minhang District, Shanghai , China

➤ Sales :

Direct +86 (21) 6401-6692

Email amall@ameya360.com

QQ 800077892

Skype [ameyasales1](#) [ameyasales2](#)

➤ Customer Service :

Email service@ameya360.com

➤ Partnership :

Tel +86 (21) 64016692-8333

Email mkt@ameya360.com