

E-Series Transformer, RF 1:1 Transmission Line 4.5 - 3000 MHz

Rev. V11

Features


- Surface mount
- 1:1 Impedance ratio
- RoHS compliant
- 260°C reflow compatible
- Available on tape and reel

Description

MACOM's ETC1-1-13TR is a 1:1 transmission Line transformer in a low cost surface mount package. Ideally suited for high volume cellular and wireless applications.



Functional Schematic



Ordering Information

Part Number	Package
ETC1-1-13TR	Tape & Reel

Pin Configuration

Pin No.	Function	
1	Primary Dot	
2	Primary	
3	Secondary	
4	Not Connected (ground)	
5	Secondary Dot	

M/A-COM Technology Solutions Inc. (MACOM) and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice. Visit www.macomtech.com for additional data sheets and product information.

1

<sup>North America Tel: 800.366.2266 / Fax: 978.366.2266
Europe Tel: 44.1908.574.200 / Fax: 44.1908.574.300
Asia/Pacific Tel: 81.44.844.8296 / Fax: 81.44.844.8298</sup>

ETC1-1-13



E-Series Transformer, RF 1:1 Transmission Line 4.5 - 3000 MHz

Electrical Specifications: $T_A = 25^{\circ}C$, $Z_0 = 50 \Omega$, $P_{in} = 0 \text{dBm}$

Parameter	Conditions	Units	Min	Тур	Max
Frequency Range		MHz	4.5		3000
Impedance		Ω		50	
Impedance Ratio				1:1	
Insertion Loss	4.5 - 1000 MHz 1000 - 2000 MHz 2000 - 3000 MHz	dB dB dB	- - -	0.32	1.0 2.0 3.5
Amplitude Balance	-	dB	-	-	±1.0
Phase Balance	-	٥	-	-	±20

Recommended Maximum Ratings

Parameter	Units	Min	Max
Input RF Power	mW		250
DC Current	mA		30
Operating Temperature Range	°C	-55	+85

Full temperature plots available on request

Tape & Reel Information

Parameter	Units	Value	
Qty per reel	-	2000	
Reel size	mm	330	
Tape width (W)	mm	12.00	
Pitch (P₁)	mm	8.00	
A ₀	mm	4.0	
B ₀	mm	4.0	
K ₀	mm	2.9	
Orientation	-	F5	
Reference Application note ANI-019 for orientation			

<sup>North America Tel: 800.366.2266 / Fax: 978.366.2266
Europe Tel: 44.1908.574.200 / Fax: 44.1908.574.300
Asia/Pacific Tel: 81.44.844.8296 / Fax: 81.44.844.8298</sup>


ETC1-1-13



E-Series Transformer, RF 1:1 Transmission Line 4.5 - 3000 MHz


Rev. V11

Outline Drawing



- 1. Dimensions in mm.
- Tolerance: ±0.2mm unless otherwise noted.
- Model number and lot code are printed on the reel.
- Lead finish: Sn

PCB Layout



M/A-COM Technology Solutions Inc. (MACOM) and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice. Visit www.macomtech.com for additional data sheets and product information.

- North America Tel: 800.366.2266 / Fax: 978.366.2266
 Europe Tel: 44.1908.574.200 / Fax: 44.1908.574.300
 Asia/Pacific Tel: 81.44.844.8296 / Fax: 81.44.844.8298



E-Series Transformer, RF 1:1 Transmission Line 4.5 - 3000 MHz


Rev. V11

Typical Performance Curves


Insertion Loss




Phase Unbalance



Input Impedance



Amplitude Unbalance



Electrical Specifications: $Z_0 = 50\Omega$, $T_A = 25$ °C, $P_{in} = 0$ dBm

M/A-COM Technology Solutions Inc. (MACOM) and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice. Visit www.macomtech.com for additional data sheets and product information.

- North America Tel: 800.366.2266 / Fax: 978.366.2266
- Europe Tel: 44.1908.574.200 / Fax: 44.1908.574.300 Asia/Pacific Tel: 81.44.844.8296 / Fax: 81.44.844.8298

ETC1-1-13



E-Series Transformer, RF 1:1 Transmission Line 4.5 – 3000 MHz

Rev. V11

M/A-COM Technology Solutions Inc. All rights reserved.

Information in this document is provided in connection with M/A-COM Technology Solutions Inc ("MACOM") products. These materials are provided by MACOM as a service to its customers and may be used for informational purposes only. Except as provided in MACOM's Terms and Conditions of Sale for such products or in any separate agreement related to this document, MACOM assumes no liability whatsoever. MACOM assumes no responsibility for errors or omissions in these materials. MACOM may make changes to specifications and product descriptions at any time, without notice. MACOM makes no commitment to update the information and shall have no responsibility whatsoever for conflicts or incompatibilities arising from future changes to its specifications and product descriptions. No license, express or implied, by estoppels or otherwise, to any intellectual property rights is granted by this document.

THESE MATERIALS ARE PROVIDED "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED, RELATING TO SALE AND/OR USE OF MACOM PRODUCTS INCLUDING LIABILITY OR WARRANTIES RELATING TO FITNESS FOR A PARTICULAR PURPOSE, CONSEQUENTIAL OR INCIDENTAL DAMAGES, MERCHANTABILITY, OR INFRINGEMENT OF ANY PATENT, COPYRIGHT OR OTHER INTELLECTUAL PROPERTY RIGHT. MACOM FURTHER DOES NOT WARRANT THE ACCURACY OR COMPLETENESS OF THE INFORMATION, TEXT, GRAPHICS OR OTHER ITEMS CONTAINED WITHIN THESE MATERIALS. MACOM SHALL NOT BE LIABLE FOR ANY SPECIAL, INDIRECT, INCIDENTAL, OR CONSEQUENTIAL DAMAGES, INCLUDING WITHOUT LIMITATION, LOST REVENUES OR LOST PROFITS, WHICH MAY RESULT FROM THE USE OF THESE MATERIALS.

MACOM products are not intended for use in medical, lifesaving or life sustaining applications. MACOM customers using or selling MACOM products for use in such applications do so at their own risk and agree to fully indemnify MACOM for any damages resulting from such improper use or sale.

5

M/A-COM Technology Solutions Inc. (MACOM) and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice.

Visit www.macomtech.com for additional data sheets and product information.

- North America Tel: 800.366.2266 / Fax: 978.366.2266
- Europe Tel: 44.1908.574.200 / Fax: 44.1908.574.300
- Asia/Pacific Tel: 81.44.844.8296 / Fax: 81.44.844.8298

AMEYA360 Components Supply Platform

Authorized Distribution Brand:

























Website:

Welcome to visit www.ameya360.com

Contact Us:

> Address:

401 Building No.5, JiuGe Business Center, Lane 2301, Yishan Rd Minhang District, Shanghai , China

Sales:

Direct +86 (21) 6401-6692

Email amall@ameya360.com

QQ 800077892

Skype ameyasales1 ameyasales2

Customer Service :

Email service@ameya360.com

Partnership :

Tel +86 (21) 64016692-8333

Email mkt@ameya360.com