



Common Mode Chokes

Stock Locator

Laird Technologies' current compensated surface mount chokes for controller area networks (CAN-Bus) in automotive and industrial controls applications.

Results 1 - 9 of 9

Item #	Figure Number	Typical Peak Impedance	Peak Impedance Frequency	Leakage (L)	Dimension A	Dimension A1
CC1812C513R-10	2	3530 ohms	40 MHz	2.6 μ H	5.00 mm 0.197 in	0.205 in 5.20 mm
CC2824B475R-10	1	12300 ohms	2 MHz	0.30 μ H	7.50 mm 0.295 in	0.354 in 9.00 mm
CC2824D225R-10	1	5278 ohms	5 MHz	0.25 μ H	7.50 mm 0.295 in	0.354 in 9.00 mm
CC2824E105R-10	1	4250 ohms	7 MHz	0.20 μ H	7.50 mm 0.295 in	0.354 in 9.00 mm
CC2824E113R-10	1	780 ohms	200 MHz	0.05 μ H	7.50 mm 0.295 in	0.354 in 9.00 mm
CC2824E253R-10	1	1971 ohms	100 MHz	1.50 μ H	7.50 mm 0.295 in	0.354 in 9.00 mm
CC2824E474R-10	1	8580 ohms	5 MHz	0.20 μ H	7.50 mm 0.295 in	0.354 in 9.00 mm
CC2824E513R-10	1	3805 ohms	50 MHz	2.0 μ H	7.50 mm 0.295 in	0.354 in 9.00 mm
CC2824J502R-10	1	388 ohms	500 MHz	0.05 μ H	7.50 mm 0.295 in	0.354 in 9.00 mm

Results 1 - 9 of 9

AMEYA360

Components Supply Platform

Authorized Distribution Brand :



Website :

Welcome to visit www.ameya360.com

Contact Us :

➤ Address :

401 Building No.5, JiuGe Business Center, Lane 2301, Yishan Rd
Minhang District, Shanghai , China

➤ Sales :

Direct +86 (21) 6401-6692

Email amall@ameya360.com

QQ 800077892

Skype ameyasales1 ameyasales2

➤ Customer Service :

Email service@ameya360.com

➤ Partnership :

Tel +86 (21) 64016692-8333

Email mkt@ameya360.com